



CSA B44.1:25/ASME A17.5-2025

Elevator and escalator electrical equipment



Legal Notice for Harmonized Standard Jointly Developed by ASME and CSA Group

Intellectual property rights and ownership

As between American Society of Mechanical Engineers ("ASME") and Canadian Standards Association (Operating as "CSA Group") (collectively "ASME and CSA Group") and the users of this document (whether it be in printed or electronic form), ASME and CSA Group are the joint owners of all works contained herein that are protected by copyright, all trade-marks (except as otherwise noted to the contrary), and all inventions and trade secrets that may be contained in this document, whether or not such inventions and trade secrets are protected by patents and applications for patents. The unauthorized use, modification, copying, or disclosure of this document may violate laws that protect the intellectual property of ASME and CSA Group and may give rise to a right in ASME and CSA Group to seek legal redress for such use, modification, copying, or disclosure. ASME and CSA Group reserve all intellectual property rights in this document.

Disclaimer and exclusion of liability

This document is provided without any representations, warranties, or conditions of any kind, express or implied, including, without limitation, implied warranties or conditions concerning this document's fitness for a particular purpose or use, its merchantability, or its non-infringement of any third party's intellectual property rights. ASME and CSA Group do not warrant the accuracy, completeness, or currency of any of the information published in this document. ASME and CSA Group make no representations or warranties regarding this document's compliance with any applicable statute, rule, or regulation.

IN NO EVENT SHALL ASME AND CSA GROUP, THEIR RESPECTIVE VOLUNTEERS, MEMBERS, SUBSIDIARIES, OR AFFILIATED COMPANIES, OR THEIR EMPLOYEES, DIRECTORS, OR OFFICERS, BE LIABLE FOR ANY DIRECT, INDIRECT, OR INCIDENTAL DAMAGES, INJURY, LOSS, COSTS, OR EXPENSES, HOWSOEVER CAUSED, INCLUDING BUT NOT LIMITED TO SPECIAL OR CONSEQUENTIAL DAMAGES, LOST REVENUE, BUSINESS INTERRUPTION, LOST OR DAMAGED DATA, OR ANY OTHER COMMERCIAL OR ECONOMIC LOSS, WHETHER BASED IN CONTRACT, TORT (INCLUDING NEGLIGENCE), OR ANY OTHER THEORY OF LIABILITY, ARISING OUT OF OR RESULTING FROM ACCESS TO OR POSSESSION OR USE OF THIS DOCUMENT, EVEN IF ASME OR CSA GROUP HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES, INJURY, LOSS, COSTS, OR EXPENSES.

In publishing and making this document available, ASME and CSA Group are not undertaking to render professional or other services for or on behalf of any person or entity or to perform any duty owed by any person or entity to another person or entity. The information in this document is directed to those who have the appropriate degree of experience to use and apply its contents, and ASME and CSA Group accept no responsibility whatsoever arising in any way from any and all use of or reliance on the information contained in this document.

ASME and CSA Group have no power, nor do they undertake, to enforce compliance with the contents of the standards or other documents they jointly publish.

Authorized use of this document

This document is being provided by ASME and CSA Group for informational and non-commercial use only. The user of this document is authorized to do only the following:

If this document is in electronic form:

- load this document onto a computer for the sole purpose of reviewing it;
- search and browse this document; and
- print this document if it is in PDF format.

Limited copies of this document in print or paper form may be distributed only to persons who are authorized by ASME and CSA Group to have such copies, and only if this Legal Notice appears on each such copy.

In addition, users may not and may not permit others to

- alter this document in any way or remove this Legal Notice from the attached standard;
- sell this document without authorization from ASME and CSA Group; or
- make an electronic copy of this document.

If you do not agree with any of the terms and conditions contained in this Legal Notice, you may not load or use this document or make any copies of the contents hereof, and if you do make such copies, you are required to destroy them immediately. Use of this document constitutes your acceptance of the terms and conditions of this Legal Notice.



Standards Update Service

CSA B44.1:25/ASME A17.5-2025 March 2025

Title: *Elevator and escalator electrical equipment*

To register for e-mail notification about any updates to this publication go to updates.csagroup.org.

The **List ID** that you will need to register for updates to this publication is **2430939**.

If you require assistance, please e-mail techsupport@csagroup.org or call 416-747-2233.

Visit CSA Group's policy on privacy at www.csagroup.org/legal to find out how we protect your personal information.

ASMENORMDOC.COM : Click to view the full PDF of ASME A17.5 CSA B44.1 2025

Canadian Standards Association (operating as “CSA Group”), under whose auspices this National Standard has been produced, was chartered in 1919 and accredited by the Standards Council of Canada to the National Standards system in 1973. It is a not-for-profit, nonstatutory, voluntary membership association engaged in standards development and certification activities.

CSA Group standards reflect a national consensus of producers and users — including manufacturers, consumers, retailers, unions and professional organizations, and governmental agencies. The standards are used widely by industry and commerce and often adopted by municipal, provincial, and federal governments in their regulations, particularly in the fields of health, safety, building and construction, and the environment.

More than 10 000 members indicate their support for CSA Group’s standards development by volunteering their time and skills to Committee work.

CSA Group offers certification and testing services in support of and as an extension to its standards development activities. To ensure the integrity of its certification process, CSA Group regularly and continually audits and inspects products that bear the CSA Group Mark.

In addition to its head office and laboratory complex in Toronto, CSA Group has regional branch offices in major centres across Canada and inspection and testing agencies in fourteen countries. Since 1919, CSA Group has developed the necessary expertise to meet its corporate mission: CSA Group is an independent service organization whose mission is to provide an open and effective forum for activities facilitating the exchange of goods and services through the use of standards, certification and related services to meet national and international needs.

For further information on CSA Group services, write to
CSA Group
178 Rexdale Boulevard
Toronto, Ontario, M9W 1R3
Canada

A National Standard of Canada is a standard developed by a Standards Council of Canada (SCC) accredited Standards Development Organization, in compliance with requirements and guidance set out by SCC. More information on National Standards of Canada can be found at www.scc.ca.

SCC is a Crown corporation within the portfolio of Innovation, Science and Economic Development (ISED) Canada. With the goal of enhancing Canada’s economic competitiveness and social wellbeing, SCC leads and facilitates the development and use of national and international standards. SCC also coordinates Canadian participation in standards development, and identifies strategies to advance Canadian standardization efforts.

Accreditation services are provided by SCC to various customers, including product certifiers, testing laboratories, and standards development organizations. A list of SCC programs and accredited bodies is publicly available at www.scc.ca.

Standards Council of Canada
600-55 Metcalfe Street
Ottawa, Ontario, K1P 6L5
Canada



Cette Norme Nationale du Canada est disponible en versions française et anglaise.

Although the intended primary application of this Standard is stated in its Scope, it is important to note that it remains the responsibility of the users to judge its suitability for their particular purpose.

™A trademark of the Canadian Standards Association, operating as “CSA Group”

National Standard of Canada American National Standard

CSA/ASME Standard

CSA B44.1:25/ASME A17.5-2025

Elevator and escalator electrical equipment



® A trademark of the Canadian Standards Association
and CSA America Inc., operating as "CSA Group"

*Approved on March 12, 2025 by ANSI
Published in March 2025 by CSA Group
A not-for-profit private sector organization
178 Rexdale Boulevard, Toronto, Ontario, Canada M9W 1R3
1-800-463-6727 • 416-747-4044*

Visit the CSA Group Online Store at www.csagroup.org/store/

*The American Society of Mechanical Engineers (ASME)
Two Park Avenue
New York, NY 10016-5990, USA
1-800-843-2763*

Visit the ASME Online Store at www.asme.org

Commitment for Amendments

This Standard is issued jointly by the American Society of Mechanical Engineers (ASME) and the Canadian Standards Association (Operating as “CSA Group”). Amendments to this Standard will be made only after processing according to the Standards writing procedures of both ASME and CSA Group.

The American Society of Mechanical Engineers (ASME)
Two Park Avenue
New York, NY 10016-5990
USA
1-800-843-2763
Visit the ASME Online Store at
www.asme.org

ISBN 978-0-7918-7746-3
Copyright © 2025 by The American Society of Mechanical Engineers (ASME)

This Standard is available for public review on a continuous basis. This provides an opportunity for additional public input from industry, academia, regulatory agencies, and the public at large.



All rights reserved. “ASME” and the above ASME symbol are registered trademarks of The American Society of Mechanical Engineers. No part of this document may be copied, modified, distributed, published, displayed, or otherwise reproduced in any form or by any means, electronic, digital, or mechanical, now known or hereafter invented, without the express written permission of ASME. No works derived from this document or any content therein may be created without the express written permission of ASME. Using this document or any content therein to train, create, or improve any artificial intelligence and/or machine learning platform, system, application, model, or algorithm is strictly prohibited.

Published in March 2025 by
CSA Group
A not-for-profit private sector organization
178 Rexdale Boulevard
Toronto, Ontario, Canada
M9W 1R3
1-800-463-6727 or 416-747-4044
Visit the CSA Group Online Store at
www.csagroup.org/store/

ISBN 978-1-4883-5266-9
ICS 91.140.90
© 2025 Canadian Standards Association

All rights reserved. No part of this publication may be reproduced in any form whatsoever without the prior permission of the publisher.

Contents

CSA Technical Committee on the Elevator Safety Code	7
ASME A17 Standards Committee on Elevators and Escalators	12
CSA B44.1/ASME A17.5 Joint Committee on Elevator and Escalator Electrical Equipment	16
Preface	18
1 Scope	21
1.1 Electrical equipment covered by this Standard	21
1.1.1 Application	21
1.1.2 Types of electrical equipment	21
1.2 Maximum voltage and ambient temperatures	21
1.3 Fire and electrical shock hazards	22
1.4 Terminology	22
1.5 Units	22
2 Reference publications, definitions, and abbreviations	22
2.1 Reference publications	22
2.2 Definitions	24
2.3 Abbreviations	27
3 Construction	28
3.1 Electrical components	28
3.2 Component without an appropriate standard	28
3.3 Circuits directly connected to a telecommunication network	28
3.4 Battery powered platform lifts and stair lifts for barrier-free access	29
3.5 Short-circuit current rating	29
3.5.1 General	29
3.5.2 Short-circuit current rating for an assembly in Canada	29
3.5.3 Short-circuit current rating for an assembly in the U.S.	29
4 Enclosure construction	29
4.1 General	29
4.1.1 Enclosure strength and rigidity	29
4.1.2 Risk of unintentional contact	29
4.2 Thickness of cast-metal enclosures for live parts	29
4.2.1 General	29
4.2.2 Minimum thickness requirements	30
4.2.3 Exceptions to minimum thickness requirements	30
4.3 Thickness of sheet-metal enclosures for live parts	30
4.3.1 Minimum thickness requirements	30
4.3.2 Exceptions to minimum thickness requirements	30
4.3.3 Supporting frame	30
5 Doors and covers	31
5.1 Securement	31

5.2	Preventing contact with live parts	31
5.3	Equipment accessible to general public (AGP)	31
6	Polymeric enclosures	31
6.1	Conduit connection test	31
6.2	Thickness	31
6.3	Polymeric enclosure requirements	31
6.3.1	Flame rating	31
6.3.2	Criteria for Flame Tests A and B	32
6.4	Polymeric materials used outside a protective or fire enclosure	32
6.4.1	Flame rating	32
6.4.2	Non-metallic plug or other closure means assembled to a sheet-metal box	32
6.5	Impact tests	33
6.6	Insulating material	33
6.7	Bonding requirements	33
6.8	Bonding conductors	33
6.9	Bonding conductor minimum size	33
7	Openings in enclosures	34
7.1	Requirements for all enclosures	34
7.1.1	Openings	34
7.1.2	Probe test	34
7.1.3	Usage of probe	34
7.1.4	Dimension of an opening	34
7.1.5	Bottom of the enclosure	34
7.1.6	Opening on the bottom of the enclosure	34
7.1.7	Wires of a screen	34
7.1.8	Metal mesh	35
7.1.9	Glass covering an observation opening and forming a part of the enclosure	35
7.2	Requirements for equipment enclosures marked in accordance with Clause 20.23	35
8	Wire-bending space	35
8.1	General	35
8.2	When a wire is restricted by a barrier or obstruction from being bent	35
8.3	Wire-bending space measurement exclusions	36
8.4	Wire size	36
9	Enclosures with environmental ratings	36
10	Protection against corrosion	36
11	Insulating material	36
11.1	General	36
11.2	Flame ratings	36
11.3	Insulating materials	36
11.4	Printed circuit board and coating	36
12	Protective devices	37
12.1	Overcurrent protection	37
12.2	Number, arrangement, and ratings or settings of protective devices	37

12.2.1	General	37
12.2.2	When a short circuit rating is greater than 10 000 A	37
12.3	Supplementary overcurrent protection	37
12.4	Disconnecting means	37
12.4.1	General	37
12.4.2	Mounting of a single throw knife switch	37
12.4.3	Using a single throw knife switch	37
12.4.4	Locking the disconnecting means	37
12.4.5	Interlock	37
12.4.6	Handle positions	38
12.4.7	Function of disconnection means	38
12.4.8	Use of a manual motor controller	38
12.4.9	Electrical requirements	38
12.5	Power from more than one source	39

13 Protection of control circuits 39

13.1	Control circuit conductor protection	39
13.2	Control circuit transformer protection	40
13.2.1	Overcurrent protection	40
13.2.2	Overcurrent protection exceptions	40
13.2.3	Secondary protection	40
13.2.4	Standard rated fuse or circuit breaker	40
13.2.5	Protection in primary circuit only	40
13.2.6	Supplementary protectors	40
13.3	Use of supplementary protectors in control circuits	41

14 Internal wiring 41

14.1	General	41
14.2	Conductors smaller than No. 24 AWG	41
14.3	Insulation between conductors	42
14.4	Protection of wiring	42
14.5	Bare live parts	42
14.6	Bare conductors	42

15 Wiring terminals and leads 42

15.1	General	42
15.2	Device current rating or hp rating	42
15.3	Minimum lead sizes	43
15.4	Field wiring terminal	43
15.5	Wire-binding screws	43
15.6	Terminal plates tapped for a wire-bending screw	43
15.7	Threading depth	43
15.8	Cord-connected equipment	43
15.8.1	General	43
15.8.2	Strain relief	43

16 Electrical spacings 44

16.1	General	44
16.2	When transient voltages are known and controlled	44
16.3	Transient suppression device	44

16.4	Maintaining electrical surfaces	44
16.5	Spacing at field wiring terminal	44
16.6	Spacings for devices with limited ratings	44
16.7	Spacings for other small devices	44
16.8	Magnetically operated switches	45
16.9	Spacings on printed circuit boards	45
16.10	Spacings for motor controllers rated more than 1 hp at 151 to 300 V	45
16.11	Spacings for motor controllers rated more than 1 hp at 51 to 150 V	45
16.12	Spacings for circuits with 50 V or less	45
16.13	Spacings on pilot light	46
16.14	Spacings on series circuit	46
16.15	Spacing on switches	46
16.16	Spacings on fuses and fuseholders	46
16.17	Ceramic, vitreous-enamel, or similar coatings	46
16.18	Spacing on parts in the OFF position	46
16.19	Enamelled or similar film-coated wires	46
16.20	Insulating barrier or liner	46
16.21	Insulating barrier or liner in addition to air space	47
16.22	Thin insulating material	47
16.23	Gaskets or seals	47
16.24	Enclosure without conduit openings or knockouts	47
16.25	Space between bare live parts and bushing	47
16.26	Spacing within components	47
16.26.1	General	47
16.26.2	Fuseholders	48
16.27	Alternative methods	48
16.27.1	General	48
16.27.2	Spacing between uninsulated live part and metal enclosure wall	48
16.27.3	Field wiring terminals	48
16.27.4	Guidelines when using CSA C22.2 No. 0.2 or ANSI/UL 840	48
17	Grounding	49
17.1	General	49
17.2	Terminations	49
17.3	Grounding conductors	49
17.4	Maximum number of conductors	49
17.5	Grounding conductor size	49
17.6	Transformers secondary grounding	49
18	Printed circuit boards	49
18.1	General	49
18.2	Printed circuit boards located in Class 2 circuits	49
18.3	Printed circuit boards located in circuits with extra-low voltage	50
19	Tests	50
19.1	General	50
19.2	Endurance	50
19.2.1	Elevator duty	50
19.2.2	Device that does not make or break current	50

19.2.3	Where elevator duty is not required	50
19.2.4	All other devices	50
19.3	Solid-state ac motor controller tests	51
19.3.1	General	51
19.3.2	Test voltage	51
19.3.3	Temperature test	51
19.3.4	Dielectric voltage withstand test	51
19.3.5	Overvoltage and undervoltage tests	51
19.3.6	Overload and endurance tests	52
19.3.7	Exception	52
19.3.8	Short-circuit test	52
19.3.9	Breakdown of components test	53
19.3.10	Verification of electronic motor overload protection test	53
19.4	Power conversion equipment	53
19.4.1	General	53
19.4.2	Temperature test	54
19.4.3	Dielectric voltage withstand test	54
19.4.4	Operation tests	54
19.4.5	Normal operation	55
19.4.6	Contactor overload	55
19.4.7	Single phasing	55
19.4.8	Inoperative blower motor	55
19.4.9	Clogged filter	55
19.4.10	Current-limiting control	56
19.4.11	Breakdown of components	56
19.4.12	Electronic motor overload protection test	56
19.4.13	Short-circuit test	58
19.5	Impact test	58
19.5.1	General	58
19.5.2	Cold impact	58
19.6	Printed circuit board coatings	58
19.6.1	General	58
19.6.2	Dielectric strength — New samples	58
19.6.3	Dielectric strength — Aged samples	59
19.6.4	Dielectric strength — After humidity conditioning	59
19.6.5	Adhesion	59
19.7	Transient voltage-surge suppression	59
19.7.1	General	59
19.7.2	Input and output	59
19.8	Compression	59
19.8.1	General	59
19.8.2	Set-up	59
19.9	Deflection	60
19.9.1	General	60
19.9.2	Set-up	60
19.10	Cord pullout	60
19.11	Crushing resistance test	60
19.11.1	General	60
19.11.2	Acceptance criteria	60

20 Marking 60

20.1	French	60
20.2	General	61
20.3	Copper or aluminum conductors	61
20.4	Electrical ratings	61
20.5	Auxiliary device	62
20.6	Polymeric enclosures	62
20.7	Manual switching means	62
20.8	Equipment with more than one source	62
20.9	Fuse replacement markings	62
20.10	Screw-type terminals	62
20.11	Oil tank	62
20.12	Enclosures with open bottoms	63
20.13	Control devices shipped in separate pieces	63
20.14	A live heat sink and other exposed parts	63
20.15	Short-circuit current rating	63
20.16	Overload relay with a replaceable current element	63
20.17	Grounding conductors No. 6 AWG or smaller	63
20.18	General caution and warning	64
20.18.1	General	64
20.18.2	Language	64
20.19	Control with dc motor ratings	64
20.20	Markings for controllers according to Clause 13.1	64
20.21	Power conversion equipment	64
20.21.1	General	64
20.21.2	Motor overload protection	64
20.21.3	Motor thermal protectors	65
20.21.4	Fuse replacement mark	65
20.21.5	Specific overcurrent protective devices	65
20.21.6	Wiring diagrams or instruction manuals	65
20.21.7	Overspeed protection	65
20.21.8	Electronic over-temperature protection	65
20.22	Controllers for platform lifts and chair lifts	65
20.23	Equipment marked with AGP	66
20.24	Controller with disconnecting means	66
20.25	Controllers for wind turbine tower elevators	66
20.26	Controllers for platform lifts or stair lifts for barrier-free access with an emergency power supply	66

Annex A (informative) — Application examples 93

Annex B (informative) — CSA Group and ASME elevator and escalator publications 99

Annex C (normative) — French marking translations 103

CSA Technical Committee on the Elevator Safety Code

D. McColl	Otis Canada Inc. Mississauga, Ontario, Canada <i>Category: Producer Interest</i>	<i>Chair</i>
C. S. Cowen	TK Elevator (Canada) Ltd. Toronto, Ontario, Canada <i>Category: Producer Interest</i>	<i>Vice-Chair</i>
C. M. Ayling	PCL Constructors Canada Inc. Mississauga, Ontario, Canada <i>Category: User/General Interest</i>	
S. Beekman	Les Produits Fraco Itée Cocoa, Florida, USA	<i>Non-voting</i>
L. Bialy	Louis Bialy and Associates LLC San Rafael, California, USA	<i>Non-voting</i>
S. Bornstein	KONE Canada Inc. Mississauga, Ontario, Canada <i>Category: Producer Interest</i>	
M. Brierley	Coldwater, Ontario, Canada	<i>Non-voting</i>
K. L. Brinkman	National Elevator Industry Inc. Eureka, Illinois, USA	<i>Non-voting</i>
D. Bruce	Alberta Municipal Affairs Edmonton, Alberta, Canada <i>Category: Regulatory Authority</i>	
K. C. Cheong	MKC Engineering Corp. Vancouver, British Columbia, Canada <i>Category: User/General Interest</i>	
M. D. Do Couto	Toronto Transit Commission Toronto, Ontario, Canada	<i>Non-voting</i>

K. Duncan	Inspection and Technical Services Winnipeg, Manitoba, Canada <i>Category: Regulatory Authority</i>	
T. Evans	UL Solutions Toronto, Ontario, Canada	<i>Non-voting</i>
P. Fraser	Government of Newfoundland and Labrador/ Service NL Mount Pearl, Newfoundland and Labrador, Canada <i>Category: Regulatory Authority</i>	
A. Ghazanchaei	Otis Canada Inc. Mississauga, Ontario, Canada	<i>Non-voting</i>
G. W. Gibson	George W. Gibson and Associates Inc. Sedona, Arizona, USA	<i>Non-voting</i>
S. Gurumurthy	KONE Canada Inc. Mississauga, Ontario, Canada	<i>Non-voting</i>
A. S. Hopkirk	Trident Elevator Company Ltd. Scarborough, Ontario, Canada <i>Category: User/General Interest</i>	
A. Irving	Alberta Elevating Devices and Amusement Rides Safety Association (AEDARSA) Calgary, Alberta, Canada	<i>Non-voting</i>
R. Isabelle	KJA Consultants Inc. Toronto, Ontario, Canada <i>Category: User/General Interest</i>	
F. Kassem	TK Elevator (Canada) Ltd. Dorval, Québec, Canada	<i>Non-voting</i>
C. Kelesis	Toronto Transit Commission Toronto, Ontario, Canada	<i>Non-voting</i>
J. W. Koshak	Elevator Safety Solutions LLC Germantown, Tennessee, USA	<i>Non-voting</i>
R. Kremer	Technical Standards and Safety Authority (TSSA) Toronto, Ontario, Canada	<i>Non-voting</i>

D. Laguerre	Schindler Elevator Corp. Toronto, Ontario, Canada <i>Category: Producer Interest</i>	
D. Lenardis	Public Service Procurement Canada Ottawa, Ontario, Canada	<i>Non-voting</i>
E. MacArthur	OTIS Canada Inc. Ottawa, Ontario, Canada <i>Category: Producer Interest</i>	
S. E. MacArthur	Government of Prince Edward Island Department of Housing, Land and Communities Charlottetown, Prince Edward Island, Canada <i>Category: Regulatory Authority</i>	
R. Marsiglio	H. H. Angus and Associates Ltd. Toronto, Ontario, Canada <i>Category: User/General Interest</i>	
P. McClare	Department of Labour and Advanced Education Dartmouth, Nova Scotia, Canada <i>Category: Regulatory Authority</i>	
E. McClaskey	International Union of Elevator Constructors Pleasant Hill, California, USA <i>Category: User/General Interest</i>	
K. L. McGettigan	Elevator Industry Work Preservation Fund Effingham, New Hampshire, USA <i>Category: User/General Interest</i>	
A. McGregor	Rooney, Irving and Associates Ltd. Ottawa, Ontario, Canada	<i>Non-voting</i>
C. McIntyre	Canadian Elevator Industry Educational Program Pickering, Ontario, Canada <i>Category: User/General Interest</i>	
D. McLellan	Technical Standards and Safety Authority (TSSA) Toronto, Ontario, Canada <i>Category: Regulatory Authority</i>	
M. Mihai	Technical Standards and Safety Authority (TSSA) Toronto, Ontario, Canada	<i>Non-voting</i>

T. Miller	Priestman Neilson and Associates Ltd. Ottawa, Ontario, Canada <i>Category: User/General Interest</i>	
R. Murphy	Garaventa Canada Ltd. Surrey, British Columbia, Canada <i>Category: Producer Interest</i>	
H. Nuri	Toronto Transit Commission Toronto, Ontario, Canada	<i>Non-voting</i>
S. Palko	Technical Safety Authority of Saskatchewan (TSASK) Regina, Saskatchewan, Canada	<i>Non-voting</i>
M. Pedram	Vertex Elevator Design Etobicoke, Ontario, Canada <i>Category: Producer Interest</i>	
H. Peelle	The Peelle Company Ltd. Brampton, Ontario, Canada <i>Category: Producer Interest</i>	
B. Potvin	National Research Council — Codes Canada Ottawa, Ontario, Canada <i>Category: User/General Interest</i>	
A. Reistetter	National Elevator and Escalator Association Mississauga, Ontario, Canada	<i>Non-voting</i>
S. Reynolds	The Peelle Company Ltd. Brampton, Ontario, Canada	<i>Non-voting</i>
E. Ryba	Public Services and Procurement Canada Ottawa, Ontario, Canada <i>Category: User/General Interest</i>	
R. Santos	Technical Safety Authority of Saskatchewan (TSASK) Regina, Saskatchewan, Canada <i>Category: Regulatory Authority</i>	
R. Scharfe	Pembroke, Ontario, Canada	<i>Non-voting</i>
P. Sorensen	Technical Safety BC Vancouver, British Columbia, Canada	<i>Non-voting</i>

K. Steeves	New Brunswick Department of Public Safety Moncton, New Brunswick, Canada <i>Category: Regulatory Authority</i>	
M. Tevyaw	MHT Codes and Consulting Specialists Burlington, Ontario, Canada	<i>Non-voting</i>
T. Thomas	Government of the Northwest Territories Yellowknife, Northwest Territories, Canada <i>Category: Regulatory Authority</i>	
E. Towson	Technical Safety BC West Kelowna, British Columbia, Canada <i>Category: Regulatory Authority</i>	
B. Virk	UT Elevator Inc. Toronto, Ontario, Canada <i>Category: Producer Interest</i>	
J. Virk	UTE Elevator Inc. Toronto, Ontario, Canada	<i>Non-voting</i>
K. Virk	UT Elevator Inc. Toronto, Ontario, Canada	<i>Non-voting</i>
M. Wu	Société de transport de Montréal (STM) Montréal, Québec, Canada <i>Category: User/General Interest</i>	
L. Yang	CSA Group Toronto, Ontario, Canada	
M. Zingarelli	MAD Elevator Inc. Mississauga, Ontario, Canada	<i>Non-voting</i>
G. Lee	CSA Group Toronto, Ontario, Canada	<i>Project Manager</i>

ASME A17 Standards Committee on Elevators and Escalators

H. E. Peelle III	The Peelle Co. Ltd. Brampton, Ontario, Canada	<i>Chair</i>
R. E. Baxter	Baxter Residential Elevators LLC Allen, Texas, USA	<i>Vice-Chair</i>
M. H. Tevyaw	MHT Codes and Consulting Specialists Burlington, Ontario, Canada	<i>Vice-Chair</i>
G. A. Burdeshaw	American Society of Mechanical Engineers (ASME) New York, New York, USA	<i>Secretary</i>
E. V. Baker	National Elevator Industry Educational Program Attleboro Falls, Massachusetts, USA	
D. L. Barker	California Division of Occupational Safety and Health Monrovia, California, USA	
J. W. Blain	Edgett Williams Consulting Group Mill Valley, California, USA	
S. Bornstein	KONE Canada Inc. Mississauga, Ontario, Canada	
P. R. Bothwell	Drake EHC Oshawa, Ontario, Canada	
K. L. Brinkman	National Elevator Industry Inc. Eureka, Illinois, USA	
R. C. Burch	Vantage/GAL Manufacturing Co. LLC Nashville, Tennessee, USA	
J. W. Coaker	Coaker & Co. PC Fairfax Station, Virginia, USA	
J. Filippone	East New Brunswick, New Jersey, USA	

R. A. Gregory	Vertex Corp. Chicago, Illinois, USA
P. Hampton	TK Elevator Atlanta, Georgia, USA
J. T. Herrity	Department of the Navy, Naval Facilities Command (NAVFAC) Washington, DC, USA
B. Horne	Otis Elevator Farmington, Connecticut, USA
D. A. Kalgren	KONE Inc. Allen, Texas, USA
J. W. Koshak	Elevator Safety Solutions LLC Germantown, Tennessee, USA
R. Kremer	Technical Standards and Safety Authority (TSSA) Toronto, Ontario, Canada
D. McColl	Otis Canada Inc. Mississauga, Ontario, Canada
D. McLellan	Technical Standards and Safety Authority (TSSA) Toronto, Ontario, Canada
A. L. Peck	Hackensack, New Jersey, USA
D. K. Prince	Motion Control Engineering Inc. Rancho Cordova, California, USA
J. S. Rearick	Rearick & Co. Inc. Kittanning, Pennsylvania, USA
V. P. Robibero	RobiberoV Consultancy LLC Houston, Texas, USA
R. S. Seymour	Robert L. Seymour & Associates Inc. Frederick, Maryland, USA
C. Shade	Ohio Department of Commerce Columbus, Ohio, USA

R. D. Shepherd	Cape May Court House, New Jersey, USA	
W. M. Snyder	VTE Solution LLC Largo, Florida, USA	
J. Xue	Shanghai Institute of Special Equipment Inspection and Technical Research Shanghai, China	<i>Delegate</i>
D. S. Boucher	KONE Inc. Allen, Texas, USA	<i>Alternate</i>
J. Carlson	J Carlson Consulting LLC Oakland, California, USA	<i>Alternate</i>
L. W. Donaldson	Department of the Navy, Naval Facilities Command (NAVFAC) Washington, DC, USA	<i>Alternate</i>
D. Griefenhagen	International Union of Elevator Constructors Hugo, Minnesota, USA	<i>Alternate</i>
J. D. Henderson	TK Elevator Middleton, Tennessee, USA	<i>Alternate</i>
N. Imbimbo	Prysmian Group Casale Monferrato, Piedmont, Italy	<i>Alternate</i>
L. Metzinger	Alimak Group USA Inc. Houston, Texas, USA	<i>Alternate</i>
D. Morris	California Division of Occupational Safety and Health Monrovia, California, USA	<i>Alternate</i>
S. P. Reynolds	The Peelle Co. Ltd. Brampton, Ontario, Canada	<i>Alternate</i>
C. Romero	Motion Control Engineering Inc. Rancho Cordova, California, USA	<i>Alternate</i>
P. S. Rosenberg	Performance Elevator Consulting LLC Milwaukee, Wisconsin, USA	<i>Alternate</i>

A. Shelton	KONE Inc. Allen, Texas, USA	<i>Alternate</i>
J. L. Stabler	Stabler Associates Inc. St. Louis, Missouri, USA	<i>Alternate</i>
H. M. Vyas	VDA Inc. New York, New York, USA	<i>Alternate</i>
G. Lee	CSA Group Toronto, Ontario, Canada	<i>Project Manager</i>

ASMENORMDOC.COM : Click to view the full PDF of ASME A17.5 CSA B44.1 2025

CSA B44.1/ASME A17.5 Joint Committee on Elevator and Escalator Electrical Equipment

M. Mueller	TK Elevator Memphis, Tennessee, USA	<i>Chair</i>
M. Mihai	Technical Standards and Safety Authority (TSSA) Toronto, Ontario, Canada	<i>Vice-Chair</i>
J. Aitamurto	KONE Corp. Hyvinkaa, Finland	
P. D. Barnhart	Underwriters Laboratories Inc. Research Triangle Park, North Carolina, USA	
G. A. Burdeshaw	American Society of Mechanical Engineers (ASME) New York, New York, USA	
J. D. Busse	Fujitec America Inc. Mason, Ohio, USA	
C. Castro	Otis Elevator Co. Florence, South Carolina, USA	
T. Evans	UL Solutions Toronto, Ontario, Canada	<i>Non-voting</i>
S. Feng	Shanghai Institute of Special Equipment Inspection and Technical Research Shanghai, China	
S. Kalola	TK Elevator Atlanta, Georgia, USA	
J. F. Kleine	Otis Elevator Co. Farmington, Connecticut, USA	
J. Ko	KONE Inc. Allen, Texas, USA	<i>Non-voting</i>

P. McDermott	Technical Standards and Safety Authority (TSSA) Toronto, Ontario, Canada	
S. Millett	Otis Elevator Co. Farmington, Connecticut, USA	
C. Ramirez	KONE Inc. Allen, Texas, USA	
R. S. Williams	Computerized Elevator Corp. Elmont, New York, USA	
L. Yang	CSA Group Toronto, Ontario, Canada	
G. Lee	CSA Group Toronto, Ontario, Canada	<i>Project Manager</i>

ASMENORMDOC.COM : Click to view the full PDF of ASME A17.5 CSA B44.1 2025

Preface

This is the seventh edition of CSA B44.1/ASME A17.5, *Elevator and escalator electrical equipment*. It supersedes the previous editions published in 2019, 2014, 2011, 2004, 1996, and 1991.

The purpose of this Standard is to reduce the risk of injury and property damage from fire and electrical shock. To this end, it is a safety standard for the design and construction of equipment to be used in conformity with the rules of the applicable elevator and electrical codes (i.e., ASME A17.1/CSA B44 and CSA C22.1, or NFPA 70).

This Standard arose from the need to have identical Canadian and U.S. requirements for this equipment, thereby enabling manufacturers to have their products certified by an approved testing laboratory in Canada or the United States and to have the certification ratified for acceptance in either country.

In 1986, an ad hoc committee on the certification of electrical equipment consisting of jurisdictional authorities, representatives of Canadian and U.S. testing laboratories, and Canadian and U.S. manufacturers began to develop a draft for submission to the ASME A17 Standards Committee on Elevators and Escalators and the CSA Technical Committee on the Elevator Safety Code. Its initial investigation consisted of a review of the industrial control standards CSA C22.2 No. 14 and ANSI/UL 508. These standards could not be used as such, due to the differences in the application of industrial control equipment and elevator equipment. It was recognized that industrial control equipment normally operates continuously for a low number of operations (about 3000/year) and at full-load current. In contrast, elevator control equipment operates intermittently for a high number of operations (about 500 000/year), and at up to 200% to 250% of full-load current in order to accelerate a mass. Further, elevator equipment is usually protected by either a locked machine room or a hoistway. The applicable portions of CSA C22.2 No. 14 and ANSI/UL 508 were then reviewed and adapted to elevator equipment. (Grateful acknowledgement is made to Underwriters Laboratories Inc. for the use of ANSI/UL 508.) Where there were differences between the UL and CSA Group standards, the more stringent requirements were used.

The following are the major changes to this edition:

- a) update to Clause [1](#), Scope;
- b) update to Clause [2.1](#), Reference publications;
- c) update to Clause [2.2](#), Definitions;
- d) addition of Clause [3.4](#), Battery powered platform lifts and stair lifts for barrier-free access;
- e) addition of Clause [3.5](#), Short-circuit current rating;
- f) update to Clause [4.2.3](#), Exceptions to minimum thickness requirements;
- g) update to Clause [5.3](#), Equipment accessible to general public (AGP);
- h) updates to Clauses [6.3.3](#), and [6.3.4](#), Flame Text A & Flame Test B;
- i) update to Clause [16.2](#), When transient voltages are unknown and controlled;
- j) update to Clause [16.27.4](#), Guidelines when using CSA C22.2 No. 0.2 or ANSI/UL 840;
- k) update to Clause [19.1](#), General;
- l) update to Clause [19.2.3](#), Where elevator duty is not required;
- m) update to Clause [19.4.11.1](#), General;
- n) update to Clause [20.22](#), Controllers for platform lifts and chair lifts;
- o) addition of Clause [20.26](#), Controllers for platform lifts or stair lifts for barrier-free access with an emergency power supply;

- p) update to Table 12, Minimum conductor spacings (creepage and clearance) for printed circuit boards;
- q) update to Table 17, Sequence of tests for solid-state ac motor controllers;
- r) update to Table 19, Sequence of tests for power-conversion equipment;
- s) update to Annex B, CSA Group and ASME elevator and escalator publications;
- t) update to Annex C, French marking translations; and
- u) addition of clause titles throughout.

This Standard has been approved by the CSA Technical Committee on the Elevator Safety Code and the ASME A17 Standards Committee on Elevators and Escalators. It is the intent of these committees to maintain a single harmonized standard by coordinating their procedures for revising and interpreting this Standard. To this end, interpretations and revisions of this Standard will not be issued without the approval of both committees.

This Standard was prepared by the CSA B44.1/ASME A17.5 Joint Committee on Elevator and Escalator Electrical Equipment, under the jurisdiction of the CSA Technical Committee on the Elevator Safety Code, the CSA Strategic Steering Committee on Mechanical Industrial Equipment Safety, and the ASME A17 Standards Committee on Elevators and Escalators, and has been formally approved by the CSA Technical Committee and the ASME A17 Standards Committee.

This Standard has been developed in compliance with Standards Council of Canada requirements for National Standards of Canada. It has been published as a National Standard of Canada by CSA Group.

This Standard has been approved by the American National Standards Institute (ANSI) as an American National Standard.

ASME Notes:

- 1) *The next edition of this Standard is scheduled for publication in 2030.*
- 2) *This standard was developed under procedures accredited as meeting the criteria for American National Standards and it is an American National Standard. The standards committee that approved the code or standard was balanced to ensure that individuals from competent and concerned interests had an opportunity to participate. The proposed standard was made available for public review and comment, which provided an opportunity for additional public input from industry, academia, regulatory agencies, and the public-at-large.*
- 3) *ASME does not “approve,” “rate,” or “endorse” any item, construction, proprietary device, or activity.*
- 4) *ASME does not take any position with respect to the validity of any patent rights asserted in connection with any items mentioned in this document, and does not undertake to insure anyone utilizing a standard against liability for infringement of any applicable letters patent, nor does ASME assume any such liability. Users of a standard are expressly advised that determination of the validity of any such patent rights, and the risk of infringement of such rights, is entirely their own responsibility.*
- 5) *Participation by federal agency representatives or persons affiliated with industry is not to be interpreted as government or industry endorsement of this standard.*
- 6) *ASME accepts responsibility for only those interpretations of this document issued in accordance with the established ASME procedures and policies, which precludes the issuance of interpretations by individuals.*
- 7) *ASME issues written replies to inquiries concerning interpretation of technical aspects of this standard. An interpretation can be rendered only in response to a request submitted through the online Inquiry Submittal Form at <http://go.asme.org/InterpretationRequest>. ASME procedures provide for reconsideration of any interpretation when or if additional information that*

might affect an interpretation is available. Further, persons aggrieved by an interpretation may appeal to the cognizant ASME committee.

Interpretations are published in the ASME Interpretations Database at <http://go.asme.org/Interpretations> as they are issued.

CSA Group Notes:

- 1) Use of the singular does not exclude the plural (and vice versa) when the sense allows.
- 2) Although the intended primary application of this Standard is stated in its Scope, it is important to note that it remains the responsibility of the users of the Standard to judge its suitability for their particular purpose.
- 3) This Standard was developed by consensus, which is defined by CSA Policy governing standardization — Code of good practice for standardization as “substantial agreement. Consensus implies much more than a simple majority, but not necessarily unanimity”. It is consistent with this definition that a member may be included in the Technical Committee list and yet not be in full agreement with all clauses of this Standard.
- 4) To submit a request for interpretation of this Standard, please send the following information to inquiries@csagroup.org and include “Request for interpretation” in the subject line:
 - a) define the problem, making reference to the specific clause, and, where appropriate, include a graphical image;
 - b) provide an explanation of circumstances surrounding the actual field condition; and
 - c) where possible, phrase the request in such a way that a specific “yes” or “no” answer will address the issue.Committee interpretations are processed in accordance with CSA Directives and guidelines governing standardization and are available on the Current Standards Activities page at standardsactivities.csagroup.org.
- 5) This Standard is subject to review within five years from the date of publication. Suggestions for its improvement will be referred to the appropriate committee. To submit a proposal for change, please send the following information to inquiries@csagroup.org and include “Proposal for change” in the subject line:
 - a) Standard designation (number);
 - b) relevant clause, table, and/or figure number;
 - c) wording of the proposed change; and
 - d) rationale for the change.

CSA B44.1:25/ASME A17.5-2025

Elevator and escalator electrical equipment

1 Scope

1.1 Electrical equipment covered by this Standard

1.1.1 Application

This Standard applies to the electrical equipment for

- a) elevators covered by ASME A17.1/CSA B44 and ASME A17.8/CSA B44.8;
- b) escalators;
- c) moving walks;
- d) dumbwaiters;
- e) material lifts;
- f) manlifts; and
- g) platform lifts and stair lifts for barrier-free access (see CSA B355), and platform lifts and stairway chairlifts (see ASME A18.1).

1.1.2 Types of electrical equipment

The electrical equipment covered by this Standard are

- a) motor controllers;
- b) motion controllers;
- c) operation controllers;
- d) operating devices; and
- e) all other electrical equipment not listed/certified and labelled/marked according to another product safety standard or code.

The equipment specified in this Standard is intended for installation in accordance with the *Canadian Electrical Code, Part 1* (CSA C22.1), and NFPA 70, whichever is applicable.

Note: *Controllers (i.e., motion, motor, and operation controllers) are defined in CSA B44 and ASME A17.1.*

1.2 Maximum voltage and ambient temperatures

The electrical equipment covered by this Standard is intended

- a) to be connected to supply circuits at a nominal system voltage of 600 V or less;
- b) for internal voltages that are not more than 1500 V;
- c) for use in non-hazardous locations in accordance with the rules of the applicable electrical codes; and
- d) for use in an ambient temperature no greater than 40 °C.

Note: *This Standard does not include requirements for equipment intended for use in an ambient temperature above 40 °C. Additional investigation of the equipment will be required when equipment is to be used in an ambient temperature above 40 °C.*

1.3 Fire and electrical shock hazards

The objective of this Standard is to reduce the risk of injury to persons and damage to property from fire and electrical shock by presenting requirements for the proper design, the good construction, and the high quality of work of the equipment listed in Clause [1.1](#).

1.4 Terminology

In this Standard, “shall” is used to express a requirement, i.e., a provision that the user is obliged to satisfy in order to comply with the Standard; “should” is used to express a recommendation or that which is advised but not required; and “may” is used to express an option or that which is permissible within the limits of the Standard.

Notes accompanying clauses do not include requirements or alternative requirements; the purpose of a note accompanying a clause is to separate from the text explanatory or informative material.

Notes to tables and figures are considered part of the table or figure and may be written as requirements.

Annexes are designated normative (mandatory) or informative (non-mandatory) to define their application.

1.5 Units

The values given in SI units are the units of record for the purposes of this Standard. The values given in parentheses are for information and comparison only.

2 Reference publications, definitions, and abbreviations

2.1 Reference publications

This Standard refers to the following publications, and where such reference is made, it shall be to the edition listed below, including all amendments published thereto.

CSA Group

CAN/CSA-B311-02 (R2018)
Safety code for manlifts

B355:19
Platform lifts and stair lifts for barrier-free access

C22.1:21
Canadian Electrical Code, Part I (25th Edition), Safety Standard for Electrical Installations

C22.2 No. 0:20
General requirements — Canadian Electrical Code, Part II

C22.2 No. 0.2:16 (R2020)
Insulation coordination

C22.2 No. 0.4:17
Bonding of electrical equipment

C22.2 No. 0.17-00 (R2018)

Evaluation of properties of polymeric materials

C22.2 No. 0.23:15 (R2020)

General requirements for battery-powered appliances

C22.2 No. 4:16 (R2020)

Enclosed and dead-front switches

C22.2 No. 5:16 (R2021)

Molded-case circuit breakers, molded-case switches and circuit-breaker enclosures

C22.2 No. 14-18 (R2022)

Industrial control equipment

C22.2 No. 66.3-06 (R2020)

Low voltage transformers — Part 3: Class 2 and Class 3 transformers

C22.2 No. 94.2:20

Enclosures for electrical equipment, environmental considerations

C22.2 No. 235:04 (R2017)

Supplementary protectors

C22.2 No. 286:23

Industrial control panels and assemblies

CAN/CSA-C22.2 No. 60950-1-07 (R2021)

Information technology equipment — Safety — Part 1: General requirements

ANSI/UL (American National Standards Institute/ULSE Inc.)

ANSI/UL 50E-2020

Enclosures for Electrical Equipment, Environmental Considerations

ANSI/UL 94-2013 (R2021)

Safety Tests for Flammability of Plastic Materials for Parts in Devices and Appliances

ANSI/UL 98-2016 (R2019)

Enclosed and Dead-Front Switches

ANSI/UL 489-2016 (R2019)

Molded-Case Circuit Breakers, Molded-Case Switches, and Circuit-Breaker Enclosures

ANSI/UL 508-2018 (R2021)

Industrial Control Equipment

ANSI/UL 508A-2018

Industrial Control Panels

ANSI/UL 746C-2018 (R2021)

Polymeric Materials — Use in Electrical Equipment Evaluations

ANSI/UL 796-2020 (R2021)

Printed Wiring Boards

ANSI/UL 840-2005 (R2016)

Insulation Coordination Including Clearances and Creepage Distances for Electrical Equipment

ANSI/UL 1077-2015 (R2021)

Supplementary Protectors for Use in Electrical Equipment

ANSI/UL 5085-3-2006 (R2017)

Low Voltage Transformers — Part 3: Class 2 and Class 3 Transformers

ANSI/UL 60950-1-2007 (R2019)

Information Technology Equipment — Safety — Part 1: General Requirements

ASME (American Society of Mechanical Engineers)

ASME A17.1-2022/CSA B44:22

Safety code for elevators and escalators

ASME A17.8-2021/CSA B44.8:21

Standard for wind turbine tower elevators

A18.1-2020

Safety Standard for Platform Lifts and Stairway Chairlifts

IEEE (Institute of Electrical and Electronics Engineers)

4-2013

IEEE Standard for High-Voltage Testing Techniques

NEMA (National Electrical Manufacturers Association)

ICS 19-2002 (R2007, R2011, R2016)

Diagrams, Devices Designations and Symbols

NFPA (National Fire Protection Association)

70-2023

National Electrical Code

2.2 Definitions

The following definitions shall apply in this Standard:

Bonding — a low impedance path obtained by permanently joining all non-current-carrying metal parts to ensure electrical continuity and having the capacity to conduct safely any current likely to be imposed on it.

Clearance distance — the shortest distance in air between two conductive parts.

Comparative tracking index (CTI) — a rating that provides an indication of the material's ability to withstand carbonization due to low level electrical current on the surface of the material.

Conformal coating — a protective covering applied on a printed circuit board capable of conforming to the configuration of objects coated and used to increase the dielectric voltage-withstand capability between conductors and/or to protect against environmental conditions.

Control circuit — a circuit that carries the electric signals directing the performance of a controller but which does not carry the main power circuit.

Controller — a device or group of devices that serves to govern in some predetermined manner the electric power delivered to the apparatus to which it is connected.

Controller, manual motor — a motor controller operated only by direct manual means.

Controller, solid-state motor — a motor controller designed to make and/or break the current in a motor circuit by means of the controlled conductivity of a semiconductor.

Creepage distance — the shortest distance along the surface of a solid insulating material between two conductive parts.

Enclosure — the outer cabinet that completely encloses live parts of an electrical apparatus to prevent personnel from accidentally contacting energized parts and to protect the equipment from physical damage.

Enclosure, fire — a part of the equipment intended to minimize the spread of fire or flames from within.

Enclosure environmental rating — an enclosure rating signifying compliance with defined environmental construction and performance requirements.

Live parts — conductive components intended to be energized during operation.

Motor circuit — the circuit that carries the main power for a motor.

Motor control circuit — the control circuit associated with a motor controller.

Opposite polarity — with respect to spacing and insulation requirements of this Standard, a difference in potential between two points, such that shorting of these two points would result in a condition involving an overcurrent; rupturing of printed wiring-board traces, components, or fuses; or similar results.

Overcurrent — any current in excess of the rated current of equipment or the ampacity of a conductor resulting from abnormal conditions. It might result from overload, short circuit, or ground fault.

Overcurrent device (or Overcurrent protective device) — a device capable of automatically opening an electric circuit, under both predetermined overload and short-circuit conditions, either by fusing of metal or by electromechanical means.

Overload — a condition that causes equipment or circuitry to exceed its effective-current (RMS) rating over its rated duty cycle. Overload currents flow within the complete intended path. Overload conditions might result from excessive mechanical or electrical loading.

Overload relay — a device used to protect motors from damage due to overheating caused by excessive current flow over a period of time by causing the motor controller to interrupt the motor current.

Overvoltage category — a grouping of products based on typical installed location with respect to overvoltage protection and available energy.

Pigtails — a length of wire, one end of which is pre-connected at the equipment manufacturer's location. The free end is intended for connection during final installation.

Pilot duty — the rating assigned to a relay or switch that controls the coil of another relay, contactor, or other similar load.

Power conversion equipment — equipment that supplies power to control a motor(s) at a frequency or voltage that is different from the input supply.

Primary battery — a battery that is the sole source of power for the circuit where the circuit does not include any recharging circuitry.

Printed circuit board (or Printed wiring board) — a board produced from rigid or flexible industrial laminate material that provides point-to-point connections and/or printed components in a predetermined arrangement.

Protection, ground-fault — a means of detecting and interrupting a ground fault current at a level less than the current required to operate the circuit overcurrent device.

Protection, overcurrent, branch circuit — a device capable of providing protection for service, feeder, and branch circuits, and equipment over the full range of overcurrent between its rated current and its interrupting rating.

Protection, overcurrent, supplementary — a device intended to provide limited overcurrent protection for specific applications and utilization equipment. This limited protection is in addition to the protection provided in the required branch circuit by the branch-circuit overcurrent protective device.

Protection, overload, motor — the protection required for motor circuits that will operate to prohibit excessive heating due to running overloads and failure to start.

Protection, short-circuit, branch circuit — a device capable of providing short-circuit protection for feeder and branch circuits and equipment, over the range of overcurrent above its rated overload current up to its rated interrupting current.

Protective device — a device used to protect an electrical circuit from an abnormal condition.

Short-circuit — unintended impedance placed directly across an electrical circuit to another element of the same circuit, to another circuit, or to ground. Short-circuit currents do not flow within the complete intended path. Short-circuit conditions result from abnormal connections and do not include normal leakage currents.

Transformer, Class 2 — a transformer complying with ANSI/UL 5085-3 or CSA C22.2 No. 66.3.

Transformer, isolating — a transformer having no electrical connection between the primary and secondary windings.

Transient suppression device — a component or assembly of components that limits the transient voltage, such as a voltage clamping device, a transformer with isolated windings, or a suitably located damping impedance or a combination of these devices.

Transient voltage not limited — a condition wherein an apparatus or circuit does not employ a component or assembly that limits the peak transient voltage.

Transient voltages, known and controlled (Transient voltage limited) — a condition wherein an apparatus or circuit employs a suitable component or assembly that limits the peak transient voltage to a specified value.

Wire-bending space — a space opposite field wiring terminals or any other space in which it is intended that field wiring may be bent or offset.

Wire-binding screw — a screw used to fasten an unprepared conductor that is looped around the shank of the screw and secured under the head of the screw or a prepared conductor that is assembled about the screw shank and retained by the head of the screw.

Wiring, field — wiring terminated at the equipment in the final installation and that is subjected to the requirements for wiring as specified in the applicable installation code.

Wiring, internal — wiring located within the equipment, installed under controlled conditions, at the equipment manufacturer's location.

Wiring terminal — an assembly that establishes a connection of one or more conductors by means of mechanical pressure.

Wiring terminal, field — a wiring terminal intended for field wiring connection.

2.3 Abbreviations

The following abbreviations shall apply in this Standard:

Abbreviation	Unit
A	ampere
ac	alternating current
AWG	American wire gauge
°C	degree Celsius
CTI	comparative tracking index
dc	direct current
deg	degree (angle)
°F	degree Fahrenheit
ft	foot
ft-lbf	foot pound force
h	hour
hp	horsepower
Hz	hertz

Abbreviation	Unit
in	inch
J	joule
K	kelvin
kcmil	kilo circular mil
kg	kilogram
kV	kilovolt
kVA	kilovolt ampere
lb	pound (mass)
lbf	pound (force)
lbf-in	pound force inch
mm	millimetre
µs	microsecond
N	newton (force)
Nm	newton metre (torque)
rms	root mean square
s	second
V	volt
VA	volt-ampere

3 Construction

3.1 Electrical components

Electrical components used in control equipment shall be suitable for the intended application and be either

- a) certified to the requirements of the pertinent standards covering such components; or
- b) specifically evaluated for the intended use.

3.2 Component without an appropriate standard

Components for electronic circuits such as solid-state devices (SCRs, diodes, etc.), resistors, and capacitors for which there are no appropriate standards may be accepted as components based on examination (quality of work, electrical spacings, etc.) and testing.

3.3 Circuits directly connected to a telecommunication network

Circuits incorporated in elevator equipment that are intended for direct connection to a hard-wired telecommunication network shall additionally comply with the requirements of CAN/CSA-C22.2 No. 60950-1 and ANSI/UL 60950-1, Clause 6.

Note: Examples of a telecommunication network are

- a) a public switched telephone network;
- b) a public data network;

- c) *an integrated services digital network (ISDN); and*
- d) *a private network with electrical interface characteristics similar to the examples in Items a) to c).*

3.4 Battery powered platform lifts and stair lifts for barrier-free access

Platform lifts and stair lifts for barrier-free access that are only battery-powered under normal operation shall additionally comply with applicable requirements from CSA C22.2 No. 0.23 or UL 2595.

3.5 Short-circuit current rating

3.5.1 General

Elevator equipment incorporating components in the motor branch circuit shall be marked with the short-circuit current rating (SCCR) according to Clause [20.15](#). The SCCR shall be determined in accordance with Clauses [3.5.2](#) and [3.5.3](#).

3.5.2 Short-circuit current rating for an assembly in Canada

In Canada, the SCCR for an assembly shall be determined

- a) by test according to Clause [19.1](#); or
- b) according to CSA C22.2 No. 286, Clause 4.13 and Annex [C](#).

3.5.3 Short-circuit current rating for an assembly in the U.S.

In the U.S., the SCCR for an assembly shall be determined

- a) by test according to Clause [19.1](#); or
- b) according to ANSI/UL 508A, Supplement SB.

4 Enclosure construction

4.1 General

4.1.1 Enclosure strength and rigidity

The enclosure of control equipment shall be constructed and assembled so that it will have the strength and rigidity necessary to resist the abuses to which it is likely to be subjected without resulting in a hazard due to reduction of spacings, loosening or displacement of parts, or other serious defects.

4.1.2 Risk of unintentional contact

An enclosure shall be constructed so as to reduce the risk of unintentional contact with enclosed electrical devices.

4.2 Thickness of cast-metal enclosures for live parts

4.2.1 General

A cast-metal enclosure shall be made of malleable iron, die-cast metal, or permanent mould cast aluminum, brass, bronze, or zinc.

4.2.2 Minimum thickness requirements

Other than as permitted in Clause 4.2.3, cast-metal enclosures shall be

- a) not less than 2.4 mm (0.094 in) thick for an area that is greater than 15 500 mm² (24 in²) or that has a dimension greater than 150 mm (6 in);
- b) not less than 1.6 mm (0.063 in) thick for an area that is 15 500 mm² (24 in²) or less and that has no dimensions greater than 150 mm (6 in). The area limitation may be obtained by the provision of suitable reinforcing ribs subdividing a larger area; and
- c) not less than 3.2 mm (0.125 in) at reinforcing ribs, door edges, and unthreaded conduit entries.

4.2.3 Exceptions to minimum thickness requirements

Thicknesses less than those required by Clause 4.2.2 may be permitted if the enclosure complies with the following requirements:

- a) the impact test of Clause 19.5 except the energy required for the ball impact is 13.56 J (10.0 ft-lbf) for all sizes;
- b) the crushing resistance test of Clause 19.11; and
- c) the conduit connection tests of CSA C22.2 No. 14 or ANSI/UL 508.

4.3 Thickness of sheet-metal enclosures for live parts

4.3.1 Minimum thickness requirements

Except as specified in Clause 4.3.2, the thickness of sheet-metal enclosures shall be not less than that specified in Tables 1 and 2 except that, at the points at which a wiring system will be connected, uncoated steel shall be at least 0.78 mm (0.032 in) thick, zinc-coated steel at least 0.88 mm (0.034 in) thick, and non-ferrous metal at least 1.16 mm (0.045 in) thick.

4.3.2 Exceptions to minimum thickness requirements

The thickness of sheet metal for enclosures at points other than those at which a wiring system will be connected need not comply with the thickness requirements of Clause 4.3.1 if the enclosure complies with the compression and deflection test requirements in Clauses 19.8 and 19.9.

Note: Tables 1 and 2 are based on a uniform deflection of the enclosure surface for any given load concentrated at the centre of the surface, regardless of metal thickness.

4.3.3 Supporting frame

With reference to Tables 1 and 2, a supporting frame shall consist of a structure of angles, channels, or folded rigid sections of sheet metal. This structure shall be rigidly attached to and have essentially the same outside dimensions as the enclosure surface, and have sufficient torsional rigidity to resist the bending moments that could be applied by the enclosure surface when it is deflected. A structure that is as rigid as one built with a frame of angles or channels is considered to have equivalent reinforcing.

Constructions without a supporting frame shall be considered to include

- a) a single sheet with single-formed flanges or formed edges;
- b) a single sheet that is corrugated or ribbed;
- c) an enclosure surface loosely attached to a frame (e.g., with spring clips); and
- d) an enclosure surface having an unsupported edge.

5 Doors and covers

5.1 Securement

A part of the enclosure, such as a door or a cover, shall be provided with the means, such as latches or screws, to firmly secure it in place. Snap-on covers of 0.1 m² (155 in²) or less may be permitted for signal fixtures operating at 30 V rms, or 42 V peak, or less, provided they meet the test requirements of Clause 6.16 of CSA C22.2 No. 14 or Clause 9 of ANSI/UL 508.

5.2 Preventing contact with live parts

Barriers shall be installed to prevent contact with live parts if inadvertent contact with bare live parts during normal service and adjustment operation is considered probable.

Note: Troubleshooting or the replacement of fuses is not considered a normal service adjustment operation with respect to control equipment, but the resetting of overload devices, adjustment of timers or switches, etc., are considered normal service operations.

5.3 Equipment accessible to general public (AGP)

Equipment enclosures that contain any portion of the motor controller, have markings in accordance with Clause 20.23, and are designed to be located outside machinery spaces, machine rooms, control spaces, or control rooms shall comply with the following:

- access to the interior of the enclosure shall only be via door(s) or panel(s) that is/are non-removable except with the use of tools or a key;
- door(s) or panel(s) shall require a key to open;
- door(s) or panel(s) shall remain mechanically attached to the enclosure when opened;
- door(s) or panel(s) shall be self-locking, such that a key is required to reopen the door(s) or panel(s) after closing; and
- door(s) or panel(s) shall not be self-closing.

Note: The key is required to meet the security requirements of ASME A17.1/CSA B44.

6 Polymeric enclosures

6.1 Conduit connection test

Polymeric enclosures shall comply with the conduit connection test of CSA C22.2 No. 14 or ANSI/UL 508.

6.2 Thickness

The thickness of a polymeric enclosure shall be such that the enclosure is sufficiently rigid to support the device and components that will be mounted on it.

6.3 Polymeric enclosure requirements

6.3.1 Flame rating

Polymeric enclosure materials shall be rated 5 VA (in accordance with CSA C22.2 No. 0.17 or ANSI/UL 94) or the enclosures shall comply with the requirements of Clause 6.3.2 after testing in accordance with Clause 6.3.3 or 6.3.4.

6.3.2 Criteria for Flame Tests A and B

To fulfill the requirements of the tests specified in Clause [6.3.3](#) or [6.3.4](#),

- a) the enclosure material shall not continue to burn for more than 60 s after the fifth application of the test flame;
- b) particles shall not drip from the test sample at any time during the test; and
- c) the material shall not be destroyed in the area of the test flame to the extent that the integrity of the enclosure is affected as determined by Clauses [4.1](#), [4.2](#), and [7.1](#).

6.3.3 Flame Test A

Enclosures shall be tested in accordance with either

- a) the 125 mm (5.0 in) flame test, "Flame Test A — 125 mm Flame Test", in Clause D.1 of CSA C22.2 No. 0.17; or
- b) the flame test for combustion-resistant materials in ANSI/UL 94.

6.3.4 Flame Test B

Enclosure material shall

- a) fulfill the requirements of the 125 mm (5.0 in) flame test, "Flame Test B — Flame Test for Combustion-Resistant Materials", in Appendix D, Clause D.2, of CSA C22.2 No. 0.17, except the maximum burning time after each application shall be 60 s; and
- b) not ignite within 15 s when subjected to the hot-wire ignition test of CSA C22.2 No. 0.17 or ANSI/UL 94.

6.4 Polymeric materials used outside a protective or fire enclosure

6.4.1 Flame rating

Polymeric enclosure materials outside a protective or fire enclosure (decorative) shall be classified HB or better.

Note: See CSA C22.2 No. 0.17 or ANSI/UL 94 for identification of the material classifications.

6.4.2 Non-metallic plug or other closure means assembled to a sheet-metal box

A non-metallic plug or other closure means assembled to a sheet-metal box as part of the enclosure shall be considered acceptable under any one of the following conditions:

- a) The maximum area is 645 mm² (1.0 in²) and the closure material is classified as V-0, V-1, or V-2.
- b) The maximum area is 645 mm² (1.0 in²), the closure material is classified as HB, and the closure complies with the flame test requirements in Clause [6.3](#).
- c) The maximum area is 5800 mm² (9 in²), the closure material is classified as V-0, V-1, V-2, or HB, and the closure material is used as a pilot light lens.
- d) The area is more than 645 mm² (1.0 in²), the closure material is classified as V-0, V-1, V-2, or HB, and the closure means complies with the flammability test of Clause [6.3](#) and the impact test requirements in Clause [6.5](#).
- e) The closure material is classified as V-0, V-1, V-2, or HB, and the closure material is used as a lens for a pilot light, lantern, position and/or direction indicator, operating devices, or other visual signaling device where voltage to ground is limited to 30 V_{rms} or 42.4 V peak and the current is limited to 5 A maximum for voltages up to 20 V_{rms}, or (100/V) A maximum for voltages over 20 V_{rms} up to 30 V_{rms}.

Note: See CSA C22.2 No. 0.17 or ANSI/UL 94 for identification of the material classifications.

6.5 Impact tests

Samples of equipment shall be subjected to the impact tests described in Clauses [19.5.1](#) and [19.5.2](#). The impact shall not

- a) reduce spacings below the minimum acceptable values;
- b) make any bare live parts or internal wiring accessible to contact;
- c) have an undue adverse effect on the insulation; and
- d) produce any other condition that can increase the risk of shock, fire, or damage to the equipment.

6.6 Insulating material

An enclosure employing insulating material, either wholly or in part, shall be provided with a suitable bonding means to ensure continuity of grounding between all conduit openings and any external metal parts that can become energized. The suitable bonding means shall be either completely fitted to the product or provided as separate parts for field installation. An enclosure designed for field assembly of the bonding means shall be provided with complete instructions to ensure proper installation. The instructions shall include the identification of the parts (see Clause [20.6](#)) and their method of installation.

6.7 Bonding requirements

Notwithstanding Clause [6.6](#), bonding shall not be required for enclosures of end-of-line auxiliary devices where there are no exposed metal parts that can become energized and where, if necessary, the enclosures are marked to indicate that only one conduit is to be connected to the enclosure.

Note: Examples of auxiliary devices include but are not limited to limit switches and push-button switches.

6.8 Bonding conductors

A separate bonding conductor shall be copper, a copper alloy, or other material suitable for use as an electrical conductor. Ferrous metal parts in the grounding path shall be suitably protected against corrosion by enamelling, galvanizing, plating, or other equivalent means. A separate bonding conductor shall

- a) be protected from mechanical damage or be located within the confines of the outer enclosure or frame; and
- b) not be secured by a removable fastener used for any purpose other than bonding. The ends of the bonding conductor shall be in metal-to-metal contact with the parts to be bonded.

6.9 Bonding conductor minimum size

The size of a separate component bonding conductor shall be not less than that specified in Table [3](#) or the size of the conductor supplying the component, whichever is smaller. Notwithstanding this requirement, the bonding conductor may be of smaller size than that specified in Table [3](#) but not less than the size of the conductor supplying the component provided the bonding complies with the requirements of the applicable bonding and grounding standards.

7 Openings in enclosures

7.1 Requirements for all enclosures

7.1.1 Openings

To reduce the likelihood of unintentional contact involving a risk of electric shock from an uninsulated live part or film-coated wire, or a risk of injury to personnel from a moving part, an opening in an enclosure shall comply with either of the following:

- a) for an opening that has a minor dimension (see Clause 7.1.4) less than 25.4 mm (1.0 in), such a part or wire shall not be contacted by the probe illustrated in Figure 1; or
- b) for an opening that has a minor dimension of 25.4 mm (1.0 in) or more, such a part or wire shall be distanced from the opening as specified in Table 4.

7.1.2 Probe test

The probe mentioned in Clause 7.1.1 and illustrated in Figure 1 shall be applied to any depth that the opening will permit. It shall be rotated or angled before, during, and after insertion through the opening to any position that is necessary to examine the enclosure.

7.1.3 Usage of probe

The probe mentioned in Clauses 7.1.1, 7.1.2, and 7.1.4 shall be used as the measuring instrument to judge the accessibility provided by an opening. The probe shall not be used as an instrument to judge the strength of a material. The probe shall be applied with a force sufficient to ensure full insertion but not greater than 11 N.

7.1.4 Dimension of an opening

With reference to the requirements in Clause 7.1.1, the minor dimension of an opening is the diameter of the largest cylindrical probe having a hemispherical tip that can be inserted through the opening.

7.1.5 Bottom of the enclosure

Other than as described in Clause 7.1.6, electrical equipment shall be so constructed that molten or flaming particles cannot fall to the surface on or over which the equipment is mounted.

7.1.6 Opening on the bottom of the enclosure

Coverings may be omitted from the bottom of a floor-mounted enclosure that is marked in accordance with Clause 20.12 if

- a) the enclosure extends to the floor, with live parts mounted in the enclosure in accordance with Table 5; or
- b) the control equipment is rated 600 V or less, the equipment enclosure is not marked in accordance with Clause 20.23, the enclosure is within 152 mm (6.0 in) of the floor, and the bare live parts of the device are not less than 152 mm (6.0 in) above the lower edge of the enclosure.

7.1.7 Wires of a screen

The diameter of the wires of a screen shall be not less than 1.3 mm (0.051 in) if the screen openings are 320 mm² (0.5 in²) or less in area, and shall be not less than 2.06 mm (0.0811 in) for larger screen openings.

7.1.8 Metal mesh

Perforated sheet steel and sheet steel employed for expanded metal mesh shall be not less than 1.07 mm (0.042 in) thick for mesh openings or perforations 320 mm² (0.5 in²) or less in area, and shall be not less than 2.03 mm (0.080 in) thick for larger openings.

In a small device, where the indentation of a guard enclosure will not alter the clearance between uninsulated, movable, and live parts and grounded metal so as to adversely affect the performance or reduce spacings below the minimum values specified in Table 5, expanded metal mesh not less than 0.51 mm (0.020 in) thick may be employed provided

- a) the exposed mesh on any one side or surface of the device has an area of not more than 46 500 mm² (72 in²) and has no dimension greater than 305 mm (12 in); or
- b) the width of an opening is not greater than 88 mm (3.5 in).

7.1.9 Glass covering an observation opening and forming a part of the enclosure

Glass covering an observation opening and forming a part of the enclosure shall be reliably secured in such a manner that it cannot be readily displaced in service and it provides mechanical protection for the enclosed parts.

Glass covering an opening not more than 100 mm (4 in) in any dimension shall be not less than 1.4 mm (0.055 in) thick, and glass covering an opening having no dimension greater than 305 mm (12 in) shall be not less than 2.92 mm (0.115 in) thick.

Glass used to cover larger openings shall be of the clear safety type or wire-reinforced type.

7.2 Requirements for equipment enclosures marked in accordance with Clause 20.23

Equipment enclosures containing any portion of the motor controller that have markings in accordance with Clause 20.23 designed to be located outside machinery spaces, machine rooms, control spaces, or control rooms shall comply with the following:

- a) there shall be no opening accessible to the public after installation;
- b) Clause 7.1.6 shall not apply; and
- c) in addition to the requirements in Clause 7.1.9, all glass covering an observation opening or forming a part of an enclosure shall be of the clear safety type or the wire-reinforced type.

8 Wire-bending space

8.1 General

The wire-bending space at a field wiring terminal shall be measured from the centre of the conductor opening on the face of the wire connector to the enclosure wall opposite the terminal, in the line in which the wire leaves the connector when the connector is at the smallest angle to the perpendicular of the enclosure wall that it can assume without defeating any reliable means provided to prevent it from turning. A connector shall not be directed toward a corner or a recess in an enclosure to obtain the required bending space. The wire-bending space shall be as specified in Table 6.

8.2 When a wire is restricted by a barrier or obstruction from being bent

If a wire is restricted by a barrier or obstruction from being bent in a single 90° or S-bend between the terminal and any permitted enclosure entrance point, the wire-bending space shall be measured from

the end of the barrier or obstruction to the wall towards which the wire is directed, in a line perpendicular to the wall.

8.3 Wire-bending space measurement exclusions

A barrier, shoulder, or the like shall be disregarded when the measurement is being made if it does not reduce the radius to which the wire must be bent.

8.4 Wire size

The wire size used to determine the wire-bending space shall be determined as described in CSA C22.2 No. 14 or ANSI/UL 508.

9 Enclosures with environmental ratings

Enclosures with an environmental rating shall comply with the requirements of CSA C22.2 No. 94.2 or ANSI/UL 50E.

10 Protection against corrosion

Ferrous metals shall be suitably protected against corrosion as required by CSA C22.2 No. 0 or ANSI/UL 508.

11 Insulating material

11.1 General

Material for the support of an uninsulated live part shall be porcelain, phenolic, cold-moulded composition, unfilled nylon, melamine, melamine-phenolic, urea formaldehyde, or other material found acceptable for the support of an uninsulated live part.

These materials shall withstand the most severe conditions likely to be met in service.

11.2 Flame ratings

The insulation material shall be classified as V-0, V-1, V-2, or HB.

Note: See CSA C22.2 No. 0-17 or ANSI/UL 94 for identification of the material classifications.

11.3 Insulating materials

Insulating material, including barriers between parts of opposite polarity and material that can be subject to the influence of the arc formed by the opening of a switch, shall be suitable for the particular application. Materials shall not be adversely affected by the overload and endurance tests.

11.4 Printed circuit board and coating

A printed circuit board and any coating material that is provided shall not increase the flammability of the assembly.

12 Protective devices

12.1 Overcurrent protection

Protective devices shall be provided for motor branch circuit overcurrent protection, ground-fault protection, and motor running overload protection where required by the applicable electrical code.

12.2 Number, arrangement, and ratings or settings of protective devices

12.2.1 General

The number, arrangement, and ratings or settings of protective devices used in control equipment shall be in accordance with the requirements of the applicable electrical code.

12.2.2 When a short circuit rating is greater than 10 000 A

If a controller has a short circuit rating of greater than 10 000 A, all branch circuit fuseholders shall be provided with rejection features to prohibit the use of Class H fuses.

12.3 Supplementary overcurrent protection

Supplementary overcurrent protection shall not be used as a substitute for required branch circuit overcurrent devices or in place of required branch circuit protection.

12.4 Disconnecting means

12.4.1 General

When provided as part of the controller, a disconnecting means shall comply with Clauses [12.4.2](#) through [12.4.9](#).

12.4.2 Mounting of a single throw knife switch

A single throw knife switch shall be mounted so that gravity will not tend to close it.

12.4.3 Using a single throw knife switch

A single throw knife switch shall be connected so that the blades will be de-energized when the switch is open unless the switch is designed so that all live parts are protected against unintentional contact when the switch is in the open position and the controller enclosure door or cover is open.

12.4.4 Locking the disconnecting means

A disconnecting means provided as a branch circuit disconnect, a local controller disconnect, or a motor disconnect shall be operable from outside the controller enclosure, and shall be capable of being locked in the open position independent of the controller door position. The provision for locking or adding a lock to the disconnecting means shall be installed on or at the switch or circuit breaker used as the disconnecting means and shall remain in place with or without the lock installed. Portable means for adding a lock to the switch or circuit breaker shall not be permitted as the means required to be installed at and remain with the equipment.

12.4.5 Interlock

If an interlock is provided between the door or cover and a switching mechanism of a disconnecting means, provision for circumventing the interlock for inspection purposes while the switch is in the ON position may be permitted.

12.4.6 Handle positions

Handle positions shall be marked as specified in Clause [20.7](#).

12.4.7 Function of disconnection means

A disconnecting means shall open all ungrounded conductors of the source that it disconnects. One pole may be permitted to disconnect a permanently grounded conductor provided the disconnecting means is designed so that the pole in the grounded conductor cannot be opened without disconnecting all conductors of the circuit in the same operation.

12.4.8 Use of a manual motor controller

If a controller includes a manual motor controller that can be locked or sealed in the open position, this manual motor controller shall be tested, approved, and marked as "Suitable for Motor Disconnect". When this device is provided, the locking means shall meet the requirements of Clause [12.4.4](#).

Notes:

- 1) *A manual motor controller is a horsepower-rated switching device with an operating mechanism, such as a pushbutton or operating handle, that is intended to be operated manually to open or close the contacts to control a motor.*
- 2) *Unless specifically tested, approved, and marked as "Suitable for Motor Disconnect", a manual motor controller has not been investigated for use as a disconnecting means to isolate the load from the line. The presence of a locking or sealing means could improperly imply that the manual controller is suitable for isolation or other lockout/tagout purposes.*

12.4.9 Electrical requirements

12.4.9.1 General

When provided as part of the controller, a disconnecting means supplied to comply with CSA C22.1, Rule 38-051, or NFPA 70, Section 620.51, shall comply with Clauses [12.4.9.2](#) through [12.4.9.8](#).

12.4.9.2 Component requirements

A disconnecting means shall be a fusible switch complying with CSA C22.2 No. 4 or ANSI/UL 98, or a circuit breaker or moulded case switch complying with CSA C22.2 No. 5 or ANSI/UL 489.

12.4.9.3 Locking

The disconnecting means shall be operable from outside the controller enclosure and capable of being locked in the open position independent of the controller door position. The provision for locking or adding a lock to the disconnecting means shall be installed on or at the switch or circuit breaker used as the disconnecting means, and shall remain in place with or without the lock installed. Portable means for adding a lock to the switch or circuit breaker shall not be permitted as the means required to be installed at and remain with the equipment.

12.4.9.4 Ungrounded main power supply conductors

The disconnecting means shall open all ungrounded main power supply conductors for

- a) the drive motor and its ventilation and control circuits; and
- b) control valve operating magnets.

The disconnecting means shall be designed so that no pole will be independently operated under normal service conditions.

12.4.9.5 Separation

Where motor branch circuit short-circuit and ground-fault protection is provided as part of the disconnecting means, the entire assembly shall be separately enclosed within the controller enclosure or located in a separate compartment.

12.4.9.6 Protection of uninsulated parts

Uninsulated parts that remain energized with the disconnecting means in the open position shall be protected against unintentional contact when the enclosure door or cover is open.

12.4.9.7 Disconnecting means for multiple drive machines

Where multiple drive machines are connected to a single elevator, escalator, moving walk, or pumping unit, there shall be one disconnecting means that disconnects

- a) all the drive motors, their ventilation and control circuits; and
- b) all the control valve operating magnets.

The disconnecting means shall be designed so that no pole will be independently operated under normal service conditions.

12.4.9.8 Emergency or standby power system

12.4.9.8.1 General

The disconnecting means shall disconnect the elevator from both the emergency or standby power system and the normal power system.

Where an additional power source that allows movement of the car is connected to the load side of the disconnecting means, the disconnecting means shall be provided with an auxiliary contact. The auxiliary contact shall meet the requirements of Clause [12.4.9.8.2](#).

12.4.9.8.2 Auxiliary contact

An auxiliary contact for the disconnecting means shall be positively opened mechanically, and the opening shall not be solely dependent on springs.

12.5 Power from more than one source

Where a controller includes a disconnecting means and parts of the controller remain energized from a source other than the one disconnected, a marking shall be provided in accordance with Clause [20.24](#).

13 Protection of control circuits

13.1 Control circuit conductor protection

Conductors of control circuits that are connected to the load side of the motor branch circuit short-circuit protective device (common control) and extend beyond the control equipment enclosure shall be protected against overcurrent, in accordance with their ampacities, by protective devices located within the controller; otherwise, the controller shall be marked in accordance with Clause [20.20](#). Additional protection or additional marking shall not be required if the rating or setting of the intended motor branch circuit short-circuit protective device is not more than 300% of the ampacity (15 A minimum) of the control circuit conductors.

13.2 Control circuit transformer protection

13.2.1 Overcurrent protection

A control circuit transformer shall be provided with one or more of the following types of overcurrent protection:

- a) individual overcurrent devices located in the primary circuit that are rated or set as specified in Table 7;
- b) secondary circuit protection rated or set at not more than 125% of the rated secondary current of the transformer, with the protection of the primary feeder circuit rated or set at not more than 250% of the rated primary current of the transformer; or
- c) coordinated thermal overload protection arranged to interrupt the primary circuit provided the primary circuit overcurrent device is rated or set at a current of not more than
 - i) six times the rated current of the transformer for transformers having not more than 6% impedance; or
 - ii) four times the rated current of the transformer for transformers having more than 6% but less than 10% impedance.

13.2.2 Overcurrent protection exceptions

Notwithstanding Clause 13.2.1, overcurrent protection need not be provided if

- a) the transformer supplies a Class 2 circuit;
- b) the transformer is rated less than 50 VA and is an integral part of the motor controller, and there is no fire hazard (emission of flame or molten material) with a short-circuit on the secondary;
- c) the primary feeder circuit overcurrent device provides the required protection; or
- d) protection is provided by other means that comply with the applicable electrical code.

13.2.3 Secondary protection

Notwithstanding Clause 13.2.1 b), if the rated secondary current of the transformer is 2 A or more, the current rating of the secondary overcurrent device may be as indicated in Line 2 or 3 of Table 7, as applicable.

13.2.4 Standard rated fuse or circuit breaker

If the rated primary current of the transformer is 9 A or more and 125% of this current does not correspond to a standard rating of a fuse or non-adjustable circuit breaker, the next higher standard rating of protective device shall be used.

13.2.5 Protection in primary circuit only

A control transformer and its primary and secondary conductors may be protected by overcurrent devices located in the primary circuit provided the

- a) transformer is single-phase and has only a two-wire (single voltage) secondary;
- b) maximum value of an intended overcurrent device is determined in accordance with Clause 13.2.1; and
- c) maximum value of an intended overcurrent device as determined in Item b) does not exceed the value of the overcurrent device obtained from Table 7 for the secondary conductor multiplied by the secondary-to-primary voltage ratio of the transformer.

13.2.6 Supplementary protectors

A supplementary protector complying with Clause 13.3 h) may be used as the primary circuit protector for transformers supplying power only for control circuits, as required by Clause 13.2.1.

13.3 Use of supplementary protectors in control circuits

Supplementary protectors may be used in the protection of control circuits if

- they are suitable for general industrial use as determined by Table 15 of CSA C22.2 No. 235 or as indicated by Use Group (UG) A of ANSI/UL 1077;
- they are a type suitable for the function intended (i.e., under-voltage trip, over-voltage trip, overload trip, etc.);
- their short-circuit rating is adequate for the circuit in which they are used;

Note: That is, a 2 kA minimum for a control circuit with an external source or when supplied by an internal single-phase control transformer as determined by the following formula:

$(\text{transformer VA rating}) / (V_s \times z)$

where

V_s = the secondary voltage of the transformer, V

z = the impedance of the transformer, %

- the contact rating is suitable to interrupt rated overload currents, as specified by the assigned OL codes and voltage ratings (see Table A.3 for an explanation of OL code applications);
- the supplementary protector has a short-circuit application code of U3, U1a, or C1a (see Table A.1 for an explanation of U and C code applications);
- the line side overcurrent protection is provided in accordance with the manufacturer's literature when the supplementary protector has a short-circuit rating code of C1a;
- the appropriate level of protection is provided, where the supplementary protector is intended to protect a component or circuit from overheating due to overload (see Table A.2 for an explanation of TC code applications); and
- a supplementary protector used as the primary protection of a control transformer has a short-circuit current rating (SC) of U3, TC3, or OL1.

Note: Power transformers are required to be protected in accordance with the local electrical codes. See CSA C22.1 or NFPA 70 for definition of "control circuit".

14 Internal wiring

14.1 General

Insulated conductors shall be types suitable for the service intended with respect to voltage, temperature, and grouping. Conductors shall be not smaller than No. 24 AWG and the temperature rating shall be not less than 90 °C unless investigation proves the suitability of other conductors.

Notes:

- The requirements of this clause apply only to the wiring furnished on or in control equipment. They do not apply to the supply wiring that is run to control equipment, to motors, or to other apparatus.
- For motor and control circuit applications, the use of Tables 8 and 9 as a guide in selecting conductor sizes for control equipment can obviate the need to perform a temperature test on the wire. Conductor sizes for other applications (e.g., heating loads) are subject to investigation.

14.2 Conductors smaller than No. 24 AWG

Notwithstanding Clause 14.1, conductors smaller than No. 24 AWG may be used for wiring of printed circuit boards and interconnecting wiring between electronic modules and sub-assemblies.

14.3 Insulation between conductors

Conductors in an assembly intended for use in a complete enclosure shall be insulated for the highest voltage normally occurring between such conductors unless

- a) the wires are grouped so as to segregate the several voltages; or
- b) the circuits involving the wires rated at the lower voltage(s) do not extend beyond the complete enclosure.

14.4 Protection of wiring

Wires shall be supported or secured or otherwise run in suitable raceways so that they will not come into contact with moving parts or rest on sharp edges or projections that can cause abrasion of the insulation. Wires shall be of flexible or extra-flexible construction where they make connections to electrical equipment mounted on a hinged door. If the flexing section of the wiring is liable to come into contact with grounded metal parts, that portion of the wiring shall be given additional protection by wrapping of tape or the equivalent, or by enclosure in non-metallic flexible tubing or conduit.

14.5 Bare live parts

Internal wiring shall not be in contact with bare live parts of opposite polarity or with bare live parts of other circuits.

14.6 Bare conductors

A bare conductor, including pigtails and coil leads, if it is not covered by acceptable insulating sleeving or tubing, shall be supported so that the spacings required elsewhere in this Standard will be maintained.

15 Wiring terminals and leads

15.1 General

Control equipment shall be provided with wiring terminals or leads for connection of conductors having an ampacity not less than the largest of the following:

- a) the ampere rating of the equipment;
- b) 125% of the full-load motor current specified in Table [10](#) or [11](#) for the horsepower rating or, in the case of power conversion equipment in which the input current is different from motor full-load current, 125% of maximum rated input current;
- c) 125% of the resistive ampere rating of the devices intended to control fixed electric space-heating equipment loads; and
- d) for equipment controlling a direct-current motor intended to be operated from a rectified single-phase power supply,
 - i) 190% of full-load current if a half-wave rectifier is used; or
 - ii) 150% of full-load current if a full-wave rectifier is used.

Note: Item d) does not apply if the product is marked in accordance with Clause [20.19](#).

15.2 Device current rating or hp rating

A device having a current rating or an hp rating with a full-load motor-running current as specified in Table [10](#) or [11](#) shall be provided with wiring terminals or leads for connections to wire of a size determined in accordance with the applicable electrical code. The size shall be based upon a wire

suitable for a temperature of 60 °C for a rating of 100 A or less, and upon a wire suitable for 75 °C for a rating greater than 100 A. The type of insulation is not specified.

Note: Higher-temperature-rated field-installed conductors may be used provided the higher-rated conductors have a cross-sectional area no smaller than the cross-sectional area that would be required if 60 °C or 75 °C conductors were used. See Clause [20.2 a\) v\)](#).

15.3 Minimum lead sizes

A lead that is intended to be spliced to a circuit conductor in the field shall be not smaller than No. 24 AWG, and the insulation, if rubber or thermoplastic, shall be not less than 0.8 mm (0.031 in) thick.

15.4 Field wiring terminal

Terminal parts for field wiring connections shall conform to the requirements of CSA C22.2 No. 0 or ANSI/UL 508 except that for a No. 10 AWG or smaller conductor, the terminal to which wiring connections are made may consist of clamps or binding screws and a terminal plate with upturned lugs or the equivalent to hold the wires in position.

15.5 Wire-binding screws

A wire-binding screw to which field wiring connections are made shall be not smaller than No. 8 except a No. 5 screw may be used at a terminal intended only for connection of a No. 14 AWG or smaller conductor and a No. 6 screw may be used at a terminal intended only for connection of a No. 12 AWG or smaller conductor.

15.6 Terminal plates tapped for a wire-binding screw

A terminal plate tapped for a wire-binding screw shall be of metal not less than 0.76 mm (0.030 in) thick for a No. 14 AWG or smaller wire, and not less than 1.27 mm (0.050 in) thick for a wire larger than No. 14 AWG. There shall be no fewer than two full threads in the plate. Two full threads shall not be required if fewer threads result in a secure connection in which the threads will not strip upon application of a 2.3 Nm (20 lbf-in) tightening torque.

15.7 Threading depth

A terminal plate formed from stock having the minimum required thickness specified in Clause [15.6](#) may have the metal extruded at the tapped hole for the binding screw to provide two full threads.

15.8 Cord-connected equipment

15.8.1 General

Control equipment intended for cord connection to the power supply shall be provided with a suitable length, size, and type of hard-usage cord (see CSA C22.1), junior hard service cord (see NFPA 70), extra-hard-usage cord (see CSA C22.1), hard service cord (see NFPA 70), or the equivalent permitted by the applicable elevator or electrical code, which shall terminate in an appropriate attachment plug.

15.8.2 Strain relief

Strain relief shall be provided so that a mechanical stress on the cord will not be transmitted to terminals, splices, or internal wiring. At the point at which the cord passes through the enclosure wall, protection shall be provided to prevent cord abrasion. The equipment shall withstand damage to the cord or conductors and shall withstand, without displacement, the test specified in Clause [19.10](#).

16 Electrical spacings

16.1 General

Except as required by Clause [16.2](#) or as permitted by Clause [16.27](#), electrical spacings in control equipment shall be not less than those specified in Table [5](#). On printed circuit boards, the spacings of Table [12](#) may apply.

16.2 When transient voltages are known and controlled

The electrical spacings in control equipment in which transient voltages are known and controlled by a suitable surge protective device shall be not less than those specified in Table [13](#), except the spacings at a field wiring terminal shall be in accordance with Table [5](#) and Clause [16.12](#).

Surge suppressors of the metal oxide varistor type shall not be permitted as overvoltage protection for the purpose of the reduction of electrical spacing in equipment and circuits that operate in the primary circuit.

16.3 Transient suppression device

The transient suppression device specified in Clause [16.2](#) shall prevent peak transient voltages from exceeding 300% of the instantaneous peak working voltage or 300 V, whichever is greater (see Clause [19.7](#)).

16.4 Maintaining electrical surfaces

With reference to the requirements in Clauses [16.2](#) and [16.3](#), control equipment shall have provision for the maintenance of clean, dry electrical surfaces, such as a suitable conformal coating on a printed circuit board, or shall have other means of protecting equipment from atmospheres containing dust.

16.5 Spacing at field wiring terminal

The spacing at a field wiring terminal shall be measured with wire connected to the terminal as in service. The connected wire for a programmable controller shall be the size that is normally required for the equipment rating. The connected wire for all devices other than a programmable controller shall be the next larger size than that normally required for the equipment rating if the terminal will accommodate it or if the equipment is not marked to restrict its use.

16.6 Spacings for devices with limited ratings

The spacings specified in Group B of Table [5](#) shall apply to

- devices rated 1 hp or equivalent FLA or less, 720 VA or less (break pilot duty), or not more than 15 A at 51 to 150 V, 10 A at 151 to 300 V, or 5 A at 301 to 600 V, or any combination thereof;
- the same devices as described in Item a) when multi-pole and controlling more than one load provided the total load connected to the line at one time does not exceed 2 hp, 1440 VA, or have a current rating greater than 30 A at 51 to 150 V, 20 A at 151 to 300 V, or 10 A at 301 to 600 V, and provided also the loading on any one pole does not exceed its marked rating; and
- manual motor controllers rated 1 hp and less.

16.7 Spacings for other small devices

The spacings in Group C of Table [5](#) apply to devices rated at 300 V or less and 1 hp or less or 2000 VA or less per pole.

Note: A switching device may also have a supplementary current rating (per pole) of 15 A or less at 51 to 150 V or 10 A at 151 to 300 V, or both.

16.8 Magnetically operated switches

The spacings of Group C of Table 5 shall also apply to magnetically operated switches that are not rated in horsepower and that have current ratings per pole not greater than 15 A at 51 to 150 V or 10 A at 151 to 300 V, or both.

16.9 Spacings on printed circuit boards

Spacings between traces of different potentials on a printed circuit board are not required to comply with Table 12 when the following conditions are met:

- The spacings are used in a circuit where power is limited by a transformer, rectifier, voltage divider, or similar device that derives power from a primary circuit, and where the short-circuit limit between conductors of the secondary circuit or between conductors and ground is 1500 VA or less.
Note: The short-circuit volt ampere limit is the product of the open-circuit volts and the short-circuit amperes, and these are rms values in an ac circuit.
- The spacings are not used for circuits containing electrical protective devices as defined in ASME A17.1/CSA B44, ASME A18.1, and CSA B355.
- The printed circuit board has a flammability rating of V-0.
- The printed circuit board base material has a minimum comparative tracking index (CTI) of 100 V.
- The traces do not involve separate isolated circuits.
- The equipment complies with the printed wiring board abnormal operation test specified in CSA C22.2 No. 14 or ANSI/UL 508.

16.10 Spacings for motor controllers rated more than 1 hp at 151 to 300 V

A motor controller rated more than 1 hp at 151 to 300 V and complying with the spacings specified in Group A of Table 5 for such rating may have an additional rating of 1 hp or less at 301 to 600 V (see Clause 16.6 for multi-pole devices).

16.11 Spacings for motor controllers rated more than 1 hp at 51 to 150 V

A motor controller rated more than 1 hp at 51 to 150 V and complying with the spacings specified in Group A of Table 5 for such rating may have an additional rating of 1 hp or less at 151 to 300 V (see Clause 16.6 for multi-pole devices).

16.12 Spacings for circuits with 50 V or less

In a circuit involving voltages of 50 V or less, other than as noted in Clause 16.14, spacings at field wiring terminals may be 3.2 mm (0.125 in) through air and 6.3 mm (0.248 in) over surface.

Spacings elsewhere may be 1.6 mm (0.063 in) through air or over surface provided the insulation and clearances between such circuits and any circuits of more than 50 V are in accordance with the requirements for the higher voltage circuit.

Spacings are not specified for a circuit involving a voltage of not more than 30 V and supplied by

- a primary battery;
- a standard Class 2 transformer; or
- a suitable combination of transformer and fixed impedance having output characteristics in compliance with those required for a Class 2 transformer.

16.13 Spacings on pilot light

For a pilot light consisting of a lampholder in series with a dropping resistor or connected to an autotransformer, the spacings shall be

- a) not less than 1.2 mm (0.047 in) between bare live parts of opposite polarity at or within a lampholder (an inherent lampholder spacing) rated 250 V or less, and not less than 3.2 mm (0.125 in) for a lampholder rated more than 250 V;
- b) not less than those specified in Table 5 or in Clause 16.12 between uninsulated live parts of opposite polarity (other than at or within the lampholder), based on the normal operating voltage existing between such parts; and
- c) not less than those specified in Table 5 between bare live parts and grounded parts, exposed non-current-carrying metal parts, or the enclosure, based on the line voltage of the pilot light circuit.

16.14 Spacings on series circuit

In a series circuit, the spacings between resistor terminals, transformer taps, and the like shall be based on the normal operating voltage existing between such parts.

16.15 Spacing on switches

In a push-button switch, selector switch, limit switch, or the like, opposite polarity shall not be considered to exist on any one pole, including switches with double-throw arrangements, but opposite polarity shall be considered to exist between poles and between live parts on adjacent units unless the parts in question are connected to the same line terminal or conductor or marked to indicate the same polarity.

16.16 Spacings on fuses and fuseholders

The spacings at fuses and fuseholders, measured with the fuses in place, shall be determined using fuses that have the maximum standard dimensions, and the spacings shall be not less than those specified in Group A of Table 5.

16.17 Ceramic, vitreous-enamel, or similar coatings

A ceramic, vitreous-enamel, or similar coating shall not be acceptable as insulation in place of spacings unless, upon investigation, the coating is found to be uniform, reliable, and otherwise suitable for the purpose.

16.18 Spacing on parts in the OFF position

If contact arms, blades, etc., in a motor controller remain connected to the motor load terminals when in the OFF position, the spacing from such parts in the OFF position to the enclosure or to exposed non-current-carrying metal parts that are isolated and/or insulated shall be not less than 3.2 mm (0.125 in) plus the spacings required otherwise.

16.19 Enamelled or similar film-coated wires

Enamelled or similar film-coated wire shall be considered a bare live part when determining compliance with the spacing requirements in this Standard.

16.20 Insulating barrier or liner

An insulating barrier or liner used as the sole separation between a bare live part and a grounded non-current-carrying metal part, including the enclosure, or between bare live parts of opposite polarity shall be of a material that is suitable for the mounting of bare live parts, and shall be not less than 0.71 mm (0.028 in) thick. Fibre less than 0.71 mm (0.028 in) thick may be used as the sole separation

between the enclosure and an uninsulated metal part electrically connected to a grounded circuit conductor.

16.21 Insulating barrier or liner in addition to air space

An insulating barrier or liner that is used in addition to an air space in place of the required spacing through air shall be not less than 0.71 mm (0.028 in) thick.

If the barrier or liner is of fibre, the air space shall be not less than 0.8 mm (0.031 in). If the barrier or liner is of other material that is not suitable for the support of bare live parts, an acceptable air space shall be provided for the application.

A barrier or liner that is used in conjunction with an air space that is not less than 1/2 of the required spacing through air may be less than 0.71 mm (0.028 in) thick but not less than 0.33 mm (0.013 in) thick if the barrier or liner

- a) is of a material that is suitable for the mounting of bare live parts;
- b) has the necessary mechanical strength if exposed or otherwise likely to be subjected to mechanical abuse;
- c) is reliably held in place; and
- d) is located so that it will not be adversely affected by operation of the equipment in service.

16.22 Thin insulating material

Insulating material having a thickness less than that specified in Clauses [16.20](#) and [16.21](#) may be used if, upon investigation, it is found to be suitable for the particular application.

16.23 Gaskets or seals

Gaskets or seals, if used to obtain the required spacings, shall be subject to investigation to determine their effectiveness in service. They shall be mounted so that they are not liable to be readily damaged and shall be securely held in position.

16.24 Enclosure without conduit openings or knockouts

For an enclosure not provided with conduit openings or knockouts, spacings of not less than the minimum specified in Clause [16.1](#) shall be provided between bare live parts and a conduit bushing installed at any location likely to be used during installation. Permanent marking on the enclosure, a template, or a full-scale drawing furnished with the device may be used to limit such locations.

16.25 Space between bare live parts and bushing

When measuring a spacing between a bare live part and a bushing installed in the knockout, it shall be assumed that the bushing has the dimensions specified in Table [14](#) and that there is a single locknut installed on the outside of the enclosure.

16.26 Spacing within components

16.26.1 General

Except as required in Clause [16.26.2](#), the spacings in a component device (e.g., snap switch, lampholder) supplied as part of control equipment, other than in a motor circuit or motor control circuit, shall be not less than the minimum spacings required for the component device or the spacings specified in Table [5](#), whichever are smaller.

16.26.2 Fuseholders

Fuseholders shall meet the spacing requirements in Table 5.

16.27 Alternative methods

16.27.1 General

As an alternative to the spacing requirements specified in Clauses 16.1 to 16.26 of this Standard, clearances and creepage distances may be permitted to be evaluated in accordance with the requirements in CSA C22.2 No. 0.2 or ANSI/UL 840 that are described in Clause 16.27.4.

16.27.2 Spacing between uninsulated live part and metal enclosure wall

The clearance between an uninsulated live part and the wall of a metal enclosure, including fittings for conduit or armoured cable, shall be as specified in Table 5.

16.27.3 Field wiring terminals

The clearance and creepage distance at field wiring terminals shall be in accordance with the requirements in Clauses 16.5 to 16.8 and Table 5.

16.27.4 Guidelines when using CSA C22.2 No. 0.2 or ANSI/UL 840

In conducting evaluations in accordance with the requirements in CSA C22.2 No. 0.2 or ANSI/UL 840, the following guidelines shall be used:

- a) Unless specified elsewhere in this Standard, the pollution degree shall be considered to be Pollution Degree 3.
- b) Equipment that operates in the direct line of the source of power to the load equipment shall be considered to be Overvoltage Category II.
- c) Pollution Degree 2 may be considered to exist on a printed circuit board between adjacent conductive material covered by any coating that provides an uninterrupted covering over at least one side and the complete distance up to the other side of conductive material.
- d) Any printed circuit board that complies with the requirements in ANSI/UL 796 shall be considered to provide a minimum comparative tracking index (CTI) of 100. The materials listed in Clause 11.1 of this Standard, or any material that complies with the requirements of Section 9.3 of ANSI/UL 796, shall be considered to provide a minimum CTI of 175.
- e) In order to fulfill the requirements for coatings of printed circuit boards used to achieve Pollution Degree 1 in accordance with CSA C22.2 No. 0.2 or ANSI/UL 840, a coating shall comply with the requirements of Section 43 of ANSI/UL 746C.
- f) Pollution Degree 1 may also be achieved at a specific printed circuit board location by application of at least a 0.79 mm (0.031 in) thick layer of silicone rubber or by potting, without air bubbles, in epoxy or potting material.
- g) The evaluation of clearances to determine equivalence with through-air spacing requirements may be conducted in accordance with Clause 5.1 of CSA C22.2 No. 0.2 or ANSI/UL 840, Section 7 Clearance A (Equivalency).
- h) The evaluation of clearances and creepage distances shall be conducted in accordance with the requirements in Clauses 5.2 and 5.3 of CSA C22.2 No. 0.2, or Sections 8 and 9 and requirements on creepage distance in ANSI/UL 840.
- i) The phase-to-ground rated system voltage used in the determination of clearances shall be the equipment-rated supply voltage rounded to the next higher value (see Table 2 of CSA C22.2 No. 0.2 or Table 8.1 in ANSI/UL 840) for all points on the supply side of an isolating transformer or all points on the entire product if no isolating transformer is provided. The system voltage used in the

evaluation of secondary circuitry may be interpolated with interpolation continued across the table for the rated impulse withstand voltage peak and clearance.

- j) Determination of the dimensions of clearance and creepage distances shall be conducted in accordance with the requirements of CSA C22.2 No. 0.2 or ANSI/UL 840.

17 Grounding

17.1 General

Control equipment shall comply with CSA C22.2 No. 0.4 or ANSI/UL 508.

17.2 Terminations

Provision for bonding and grounding of control equipment shall be provided by terminations in enclosures in accordance with Clause [17.3](#).

17.3 Grounding conductors

Grounding terminations shall be provided for at least the following number of grounding conductors:

- a) in power device enclosures, one grounding conductor for each incoming and each outgoing power circuit based on one circuit for three poles or less and one circuit for each additional three poles or less, plus one grounding conductor for the control circuit where applicable;
- b) in cast enclosures for power devices that have provision for only one conduit entry, one grounding conductor; and
- c) in auxiliary device enclosures, one grounding conductor.

Note: Examples of auxiliary devices include, but are not limited to, limit switches and push-button switches.

17.4 Maximum number of conductors

The maximum number of conductors on each termination shall be in accordance with Table [15](#).

17.5 Grounding conductor size

For determining the suitability of the grounding termination, the grounding conductor size shall be

- a) No. 14 AWG copper or No. 12 AWG aluminum for control circuits and auxiliary devices; or
- b) selected from Table [16](#) for power circuits and devices.

17.6 Transformers secondary grounding

Means shall be provided to facilitate grounding of the secondaries of control circuit transformers.

18 Printed circuit boards

18.1 General

Printed circuit boards shall comply with applicable printed circuit board requirements, and shall be classed V-0, V-1, and V-2.

Note: See CSA C22.2 No. 0.17 or ANSI/UL 94 for identification of the material classifications.

18.2 Printed circuit boards located in Class 2 circuits

Notwithstanding Clause [18.1](#), a printed circuit board powered from an isolated secondary circuit of a Class 2 transformer or in an isolated secondary circuit of a transformer operating at not more than

30 V_{rms} or 42.4 V_{peak} and having a maximum capacity of 100 VA need not be classed as minimum V-2 and may be classed HB.

Note: See CSA C22.2 No. 0.17 or ANSI/UL 94 for identification of the material classifications.

18.3 Printed circuit boards located in circuits with extra-low voltage

If a printed circuit board is intended for connection only in circuits operating at not more than 30 V_{rms} or 42.4 V_{peak}, and having a maximum capacity of 100 VA, then the only requirement for the printed circuit board material is a minimum flammability rating of HB.

19 Tests

19.1 General

The temperature, overload, endurance, overvoltage, undervoltage, short-circuit, calibration, and dielectric voltage withstand tests of CSA C22.2 No. 14 or ANSI/UL 508 shall be conducted as necessary, as well as the applicable tests in Clauses [19.2](#) to [19.11](#).

19.2 Endurance

19.2.1 Elevator duty

Other than as noted in Clauses [19.2.2](#) and [19.2.3](#), electromagnetic devices (e.g., armature, across-the-line, reduced voltage) that directly control an elevator's ac or dc drive motors shall perform acceptably when subjected to an endurance test that involves making and breaking two times the current corresponding to the horsepower rating of the device for 500 000 operations. For dc-rated devices, the load shall be a non-inductive resistive load. For ac-rated devices, the load shall have a power factor of 0.4 to 0.5. The cycle rate shall be 1 s on and 9 s off except the number of cycles per minute may be increased at the manufacturer's option. The endurance test shall be conducted following the overload test of Clause [19.1](#).

19.2.2 Device that does not make or break current

A controller that has the device's coil circuit interlocked or sequenced such that in normal operation the device does not make or break current shall be tested as described in Clause [19.2.1](#) except the test current shall only be applied during the last five operations.

19.2.3 Where elevator duty is not required

Electromagnetic devices used in wind turbine tower elevators, platform lifts, and stair lifts for barrier-free access (see CSA B355), as well as electromagnetic devices used in platform lifts and stairway chairlifts (see ASME A.118.1), shall perform acceptably when subjected to the applicable endurance test of CSA C22.2 No. 14 or ANSI/UL 508. The endurance test shall be required for across the line motor starting and devices rated in horsepower, including following the electrical endurance cycles with 5000 no-load mechanical operations.

19.2.4 All other devices

All other devices shall perform acceptably when subjected to the applicable endurance test of Clause [19.1](#).

19.3 Solid-state ac motor controller tests

19.3.1 General

The performance of a solid-state motor controller shall be investigated by subjecting a representative sample or samples in commercial form to the tests indicated in Clause [19.3](#). Tests shall be conducted in the sequence specified in Table [17](#). Consideration shall be given to heat-sink capability, solid-state device ratings, and other criteria when determining which samples to use for testing a line of similarly constructed controllers.

19.3.2 Test voltage

Tests shall be conducted at rated frequency at a test voltage not less than 120, 208, 240, 277, 480, or 600 V, as appropriate for the voltage rating, except that the tests in Clauses [19.3.3](#) and [19.3.4](#) may be conducted at a voltage between 90% and 110% of the voltage specified if

- a) the current load is adjusted to produce the maximum normal heating; and
- b) the power semiconductors are capable of conduction as intended at the test voltage.

19.3.3 Temperature test

19.3.3.1 Acceptance criteria

When operating in the normal mode resulting in maximum heating and as described in Clauses [19.1](#) and [19.3.3.2](#), solid-state motor controllers shall not

- a) attain a temperature high enough to constitute a risk of fire;
- b) adversely affect any materials or components employed in the device; or
- c) exceed, at stabilized temperature, the temperature rises specified in Table [18](#).

19.3.3.2 Junction temperature

For the purpose of evaluating the temperature limit of the material, insulating material that is used at the junction in lieu of required spacings shall be considered to be at the junction temperature. To determine the insulating material temperature, reference temperatures (i.e., case, tab, heat-sink, or similar) shall be measured and the junction temperature shall be calculated based on the semiconductor manufacturer's power dissipation and thermal data.

19.3.4 Dielectric voltage withstand test

The dielectric voltage withstand test described in Clause [19.1](#) shall be conducted immediately after the temperature test with the sample at stabilized temperature and, where necessary, the power semiconductor (in the power circuit) shorted. If placement of thermocouples can adversely affect the results of the dielectric voltage withstand test, the test may be conducted on a sample without thermocouples that has been operated as specified for the temperature test until the temperature has stabilized.

19.3.5 Overvoltage and undervoltage tests

A control that employs an electromagnet shall comply with the overvoltage and undervoltage tests described in Clause [19.1](#).

19.3.6 Overload and endurance tests

A solid-state motor controller shall comply with the overload and endurance tests for reduced-voltage motor starting or across-the-line motor starting, as appropriate, in accordance with CSA C22.2 No. 14 or ANSI/UL 508.

19.3.7 Exception

Notwithstanding Clause [19.3.6](#), the endurance test need not be conducted if the test current is the same as the rated current or if there is no inrush current.

19.3.8 Short-circuit test

19.3.8.1 Compliance

Solid-state motor controllers shall comply with the following after the test described in Clauses [19.3.8.3](#) to [19.3.8.6](#):

- a) The cotton indicator shall not have ignited.
- b) The fuse connected between the live pole and the enclosure or equipment dead metal shall not have opened.
- c) The door or cover shall not be blown open, and it shall be possible to open the door or cover. Deformation of the enclosure is acceptable but shall not result in the accessibility of live parts as determined by the use of the rods specified in Clauses [19.8](#) and [19.9](#).
- d) Wires shall not be pulled out of connectors, and the wire insulation shall not burn out.

19.3.8.2 Selection of samples

A sufficient number of samples considered representative of a product line shall be subjected to short-circuit tests. Representative samples shall be selected on the basis of such features as configuration and ratings.

19.3.8.3 Test procedures

19.3.8.3.1 General

Open equipment shall be tested in an enclosure judged to be representative of that likely to be encountered when the equipment is in service. Tests may be conducted without an enclosure and considered equivalent to tests conducted using an enclosure if such testing is agreeable to those concerned. If tests are to be conducted without an enclosure, surgical cotton shall be placed on a wire cage that surrounds and is close to the equipment under test so as to closely simulate the intended enclosure.

19.3.8.3.2 Fuse in bonding circuit

The enclosure or grounded metal parts of open equipment shall be connected through a non-time-delay, 30 A cartridge fuse to the live pole judged least likely to arc to ground. The fuse shall have an interrupting rating at least equal to the short-circuit-withstand test current in the short-circuit test of Clause [19.1](#). The connection shall be made to the load side of the limiting impedance by a No. 10 AWG copper wire that is 1.2 to 1.8 m (4 to 6 ft) long.

19.3.8.3.3 Bonding wires

Notwithstanding Clause [19.3.8.3.2](#), the connection of the enclosure or grounded metal parts of open equipment may be made with No. 12 or 14 AWG copper wire if the branch-circuit conductors are No. 12 or 14 AWG, respectively.

19.3.8.4 Equipment in an outer enclosure

When testing equipment inside an outer enclosure, surgical cotton shall be placed at all openings, handles, flanges, joints, or the like, on the outside of the enclosure.

19.3.8.5 Protective devices

A short-circuit protective device that has not been investigated and determined to be reliable shall be defeated during the test.

19.3.8.6 Test circuit conditions

The test circuit conditions for the short-circuit shall be as described in Clause [19.1](#).

19.3.9 Breakdown of components test

19.3.9.1 General

A solid-state motor controller under test shall comply with the requirements in Clause [19.4.11](#).

19.3.9.2 Unacceptable conditions

With reference to Clause [19.3.9.1](#), each of the following conditions shall be unacceptable:

- a) asymmetrical switching other than half-wave;
- b) half-wave operation for a single-phase controller rated less than 5 hp; and
- c) the transmitting of one cycle or more of voltage source to the motor with the control in the OFF position, thus permitting possible rotation of a de-energized motor.

19.3.10 Verification of electronic motor overload protection test

A solid-state motor controller with integral electronic motor overload protection shall comply with the requirements of Clause [19.4.12](#) and be marked in accordance with Clause [20.21.2](#) a). Drives not incorporating integral electronic overload protection shall be marked in accordance with Clause [20.21.2](#) b) or [20.21.3](#).

19.4 Power conversion equipment

19.4.1 General

19.4.1.1 Samples

The performance of power conversion equipment shall be investigated by subjecting a representative sample or samples in commercial form to the tests described in Clauses [19.4.1.2](#) to [19.4.11](#). The tests shall be as specified in Table [19](#) and conducted in the sequence outlined in that table. Consideration shall be given to heat-sink design, solid-state device ratings, and other design criteria when selecting samples to use for testing a line of similarly constructed devices.

19.4.1.2 Testing frequency and voltage

Tests shall be conducted at rated frequency and a test voltage not less than 120, 208, 240, 277, 480, or 600 V, as appropriate for the voltage rating except the tests in Clauses [19.4.2.1](#) to [19.4.2.3](#) may be conducted at a voltage between 90% and 110% of the voltage specified if the load current is adjusted to produce the maximum normal heating.

19.4.1.3 Load

Power conversion equipment intended to control a variable-speed motor load shall be tested controlling

- a) a load equivalent to that of a motor with voltage, frequency, and current ratings corresponding to the marked rating; or
- b) a test motor capable of being loaded to the values specified.

19.4.1.4 Load simulation

Notwithstanding Clause [19.4.1.3](#), the test motor may be simulated by a passive load consisting of resistive or inductive loads.

19.4.2 Temperature test

19.4.2.1 General

When operating in the normal mode resulting in maximum heating, power conversion equipment shall not attain a temperature high enough to

- a) constitute a risk of fire;
- b) adversely affect any materials or components employed in the device; or
- c) exceed, at stabilized temperatures, the temperature rises specified in Table [18](#).

19.4.2.2 Insulating materials in lieu of required spacings

For insulating materials at semiconductor junctions that are used in lieu of required spacings, see the requirements in Clause [19.3.4](#).

19.4.2.3 Field wiring

The size of a conductor that represents field wiring in the temperature test shall be based on the rms value of the current.

19.4.3 Dielectric voltage withstand test

The dielectric voltage withstand test described in Clause [19.1](#) shall be conducted immediately after the temperature test with the sample at stabilized temperature. If placement of thermocouples can adversely affect the results of the dielectric voltage withstand test, the test may be conducted on a sample without thermocouples that has been operated as specified in the temperature test until the temperature has stabilized.

19.4.4 Operation tests

19.4.4.1 General

During and upon completion of the operation tests in Clauses [19.4.5](#) to [19.4.10](#) and [19.4.12](#), the power conversion equipment shall be electrically and mechanically operable, and there shall be no evidence of

a risk of fire or electrical shock. The fuse specified in Clause [19.4.4.2](#) shall not open, and the surgical cotton specified in Clause [19.3.8.3.1](#) or [19.3.8.4](#), whichever is applicable, shall not glow or flame.

19.4.4.2 Grounding

To assess the risk of electric shock, the outer enclosure (if any) and grounded or exposed dead metal parts shall be connected through a 30 A fuse to the supply circuit pole least likely to arc to ground. For grounded control circuits, the enclosure and grounded or exposed dead metal parts shall be connected through the 30 A fuse to ground. To assess the risk of fire, the procedures specified in Clauses [19.3.8.3.1](#) to [19.3.8.4](#) shall be followed.

19.4.4.3 Set-up

Before all operation tests, the test sample shall be mounted, connected, and operated as described in the temperature test in Clauses [19.4.1](#) and [19.4.2](#).

19.4.5 Normal operation

19.4.5.1 General

Power conversion equipment that has a rheostat, a potentiometer, or a similar device intended for operator control shall be subjected to 100 operations under the most severe normal conditions for which the control is intended.

19.4.5.2 Motor loads

The procedure described in Clause [19.4.5.1](#) is intended to demonstrate the ability of the device to control and sequence the circuit under normal conditions of operation. For motor loads, this includes starting and running with the motor loaded to full load at normal speed.

19.4.6 Contactor overload

A contactor that has the coil circuit interlocked or sequenced in such a way that in normal operation the contactor does not make or break load current shall be tested at the maximum current permitted by the current-limiting control, if provided, but at least at 150% of full-load current. Five operations shall be conducted.

19.4.7 Single phasing

Three-phase power conversion equipment shall be operated with one line disconnected at the input. The disconnected line shall be the one determined to be the line to which any protective devices are the least responsible. The test shall be conducted by disconnecting one line with the power conversion equipment operating at maximum normal load, and shall be repeated by initially energizing the device with one lead disconnected.

19.4.8 Inoperative blower motor

Power conversion equipment having forced ventilation shall be operated at rated load with inoperative blower motor(s) until the test is terminated by a protective device or until the temperature stabilizes.

19.4.9 Clogged filter

Enclosed power conversion equipment having filtered ventilation openings shall be operated with the openings blocked to represent clogged filters. The test shall be conducted initially with the ventilation

openings blocked approximately 50%. The test shall be repeated with the ventilation openings fully blocked until terminated by a protective device or the temperature stabilizes.

19.4.10 Current-limiting control

Power conversion equipment incorporating a current-limiting control shall be operated with the load increased to cause the power conversion equipment to operate in the current-limiting mode. If the current-limiting control is adjustable, it shall be adjusted to the setting producing the most severe results. The duration of the test shall not exceed the maximum time required for operation of the overload protective device or system supplied or specified on the marking required by Clause [20.21](#).

19.4.11 Breakdown of components

19.4.11.1 General

There shall be no emission of flame or molten metal nor ignition of cotton loosely placed over all openings of ventilated equipment or surrounding open devices when passive devices (e.g., capacitors and resistors) or solid-state components (e.g., transistors and diodes) are short- or open-circuited.

19.4.11.2 Exceptions

Notwithstanding Clause [19.4.11.1](#), the test shall not be required

- a) if circuit analysis indicates that no other component or portion of the circuit will be damaged as a result of the assumed open-circuiting or short-circuiting of a component;
- b) on power semiconductor devices if equivalent testing is accomplished during short-circuit tests; or
- c) for components complying with requirements applicable to the component.

19.4.12 Electronic motor overload protection test

19.4.12.1 Electronic motor overload protection

Power conversion equipment incorporating integral electronic overload protection shall comply with the electronic motor overload protection test and be marked in accordance with Clause [20.21.2](#) a). Drives not incorporating integral electronic overload protection shall be marked in accordance with Clause [20.21.2](#) b) or [20.21.3](#).

19.4.12.2 Sample

One representative sample of equipment provided with electronic motor overload protection shall be tested.

19.4.12.3 Acceptance criteria

The motor overload protection shall operate in accordance with the following conditions:

- a) ultimately at 100% of the rated tripping current;
- b) within 8 min
 - i) at 200% of the rated tripping current; or
 - ii) when the overload protection operates prior to reaching 200% overload; and
- c) within 20 s
 - i) at 600% of the rated tripping current; or
 - ii) when the overload protection operates prior to reaching 600% overload.

19.4.12.4 Resetting conditions

For accuracy, overload protective circuitry or software programs shall be reset to their zero or starting value after each test specified in Clause [19.4.12.3](#). Where provided, thermal protective devices shall be cooled to ambient after each test.

19.4.12.5 Current limit setting

The current limit setting shall be adjusted to its highest rated value that can be obtained at the motor full-load ampere setting.

19.4.12.6 Electronic motor over-temperature protection test

19.4.12.6.1 General

Power conversion equipment incorporating integral electronic over-temperature protection shall comply with the electronic motor over-temperature protection test as specified in Clauses [19.4.12.6.2](#) to [19.4.12.6.8](#). Power conversion equipment not incorporating integral electronic over-temperature protection shall be marked in accordance with Clause [20.21.3](#) or [20.21.8](#).

19.4.12.6.2 Thermal memory reset

With the thermal memory reset, the drive shall be operated and an overload condition introduced. The elapsed time between the start of the overload condition and the operation of the overload protection shall be recorded.

19.4.12.6.3 Restart

After the operation of the over-temperature protection, the drive shall be restarted and the same overload condition introduced. The elapsed time between the start of the overload condition and the operation of the overload protection shall be recorded and shall be less than the time recorded in Clause [19.4.12.6.2](#).

19.4.12.6.4 Drive set-up

With the thermal memory reset, the drive shall be operated and an overload condition introduced. The elapsed time between the start of the overload condition and the operation of the overload protection shall be recorded.

19.4.12.6.5 Power removal

After the operation of the over-temperature protection as specified in Clause [19.4.12.6.4](#), power shall be removed from the drive until all control logic functions cease to operate, with the exception of those intentionally powered by a source independent of the supply mains, such as a battery.

19.4.12.6.6 Restoring power

Power shall be restored to the drive, and the drive shall be restarted and the same overload condition introduced. The elapsed time between the start of the overload condition and the operation of the overload protection shall be recorded and shall be less than the time recorded in Clause [19.4.12.6.4](#).

19.4.12.6.7 Drive output test 1

With the thermal memory reset, the output of the drive shall be adjusted such that it will operate at 20% of rated speed and an overload condition shall then be introduced. The elapsed time between the start of the overload condition and the operation of the overload protection shall be recorded.

19.4.12.6.8 Drive output test 2

With the thermal memory reset, the output of the drive shall be adjusted such that it will operate at 10% of rated speed and an overload condition shall then be introduced. The elapsed time between the start of the overload condition and the operation of the overload protection shall be recorded and shall be less than the time recorded in Clause [19.4.12.6.7](#).

19.4.13 Short-circuit test

The power conversion equipment shall comply with Clause [19.3.8](#).

19.5 Impact test

19.5.1 General

Each of three samples of the equipment shall be subjected to an impact test on any surface that can be exposed to a blow during normal use or installation.

For an enclosure having no surface area exceeding 25 800 mm² (40 in²), the impact shall be 6.78 J (5.0 ft-lbf), produced by dropping a steel sphere 51 mm (2.0 in) in diameter and weighing 0.53 kg (1.17 lb) from a height of 1300 mm (51 in).

For an enclosure having any surface area greater than 25 800 mm² (40 in²), the impact shall be 13.56 J (10.0 ft-lbf), produced by dropping a steel sphere 51 mm (2.0 in) in diameter and weighing 0.53 kg (1.17 lb) from a height of 2600 mm (102 in).

The impact shall not result in any of the conditions specified in Clause [6.5](#).

Tests shall be conducted at any ambient temperature within the range of 10 to 40 °C (50 to 104 °F).

19.5.2 Cold impact

Each of three samples of the equipment shall be cooled to 0 °C (32 °F) and maintained at that temperature for 3 h. Immediately following removal from the cold chamber, the sample shall be subjected to the impact test in Clause [19.5.1](#).

19.6 Printed circuit board coatings

19.6.1 General

For printed circuit boards that rely on a coating for reduction of spacings in accordance with Table [12](#), the suitability of the coating shall be determined by subjecting three samples to the tests specified in Clauses [19.6.2](#) to [19.6.5](#).

19.6.2 Dielectric strength — New samples

The samples shall be conditioned by flexing them slightly four times to simulate conditions that can normally be expected.

A voltage of 1000 V plus twice the rated voltage shall be applied for 1 min without breakdown between adjacent printed circuits where there are reduced spacings.

19.6.3 Dielectric strength — Aged samples

The same samples shall then be conditioned again by maintaining them at 90 ± 1 °C (194 ± 2 °F) for 96 h and then flexing them as described in Clause [19.6.2](#). They shall then be subjected to the dielectric strength test described in Clause [19.6.2](#).

19.6.4 Dielectric strength — After humidity conditioning

The same samples shall then be conditioned again by maintaining them at 23 ± 1 °C (73 ± 2 °F) and $96 \pm 2\%$ relative humidity for 96 h and then flexing them as described in Clause [19.6.2](#). They shall then be subjected to the dielectric strength test described in Clause [19.6.2](#).

19.6.5 Adhesion

Following the tests described in Clauses [19.6.2](#) to [19.6.4](#), the samples shall be investigated for adhesion of the coating to the board by scraping or cutting. The coating shall not flake.

19.7 Transient-voltage-surge suppression

19.7.1 General

A transient voltage limited circuit as specified in Clauses [16.2](#) and [16.3](#) and Table [12](#) shall withstand without breakdown a single 1.2×50 μ s full-wave impulse with a crest value of 5.0 kV (see IEEE 4). The transient voltage surge shall not exceed 300% of the peak working voltage or 300 V, whichever is greater, and the equipment shall be operational upon completion of the test.

19.7.2 Input and output

The equipment shall be connected to a single-phase source of supply, operating at rated voltage, with the output of the impulse generator connected across the equipment.

19.8 Compression

19.8.1 General

As required by Clause [4.3.2](#), an enclosure constructed of metal that is thinner than that specified in Tables [1](#) and [2](#) shall be reinforced so that its deflection is not more than that of a reference sheet-metal enclosure of the maximum length and width constructed of the minimum required sheet-metal thickness.

19.8.2 Set-up

The enclosure shall rest on a flat, unyielding horizontal surface. A vertical force shall be applied at any point on the surface of the enclosure except for the door or cover, using a flat face of a steel bar having a 13 mm (0.5 in) square cross-section. Force shall be applied to the end, the side, and the rear walls of each enclosure. The value of the force and the limit of deflection, both of which shall be measured and recorded, are not specified, but the force on each wall of both the test and reference enclosures shall be sufficient to result in a measurable deflection of the test enclosure.

19.9 Deflection

19.9.1 General

As required by Clause [4.3.2](#), a drawn, embossed, flanged, or similarly strengthened door, front, or cover made of metal having a thickness less than that specified in Tables [1](#) and [2](#) shall not deflect inward more than 6.4 mm (0.25 in) when a vertical force of 445 N (100 lbf) is applied at any point on the door, front, or cover.

19.9.2 Set-up

The force shall be applied through a flat face of a steel bar having a 13 mm (0.5 in) square cross section. The test shall be conducted with the door, front, or cover mounted on the box in the intended manner, and the enclosure placed with its back on a flat, unyielding horizontal surface.

19.10 Cord pullout

As required by Clause [15.8.2](#), a direct pull of 156 N (35 lbf) shall be applied to the cord for 60 s. Supply connections within the equipment, if provided, shall be disconnected from terminals or splices during the test.

19.11 Crushing resistance test

19.11.1 General

Three samples of equipment shall be supported on the mounting side by a fixed rigid supporting surface, in the position that is recommended by the manufacturer. Crushing force shall be applied to the exposed surfaces of the enclosure. The compression force shall be applied by flat surfaces each 102 × 254 mm (4 × 10 in). Each force applicator shall exert 440 N (100 lbf) on the sample for 1 min. As many applicators shall be applied as the sample can accommodate, up to a maximum of 8, based upon an arrangement of applicators as indicated in Figure [2](#).

19.11.2 Acceptance criteria

The test shall be considered successful if at the conclusion none of the following occur:

- Spacings are reduced below the minimum acceptable values.
- Bare live parts or internal wiring are made accessible to contact.
- Breakage, cracking, rupture, and the like produce an adverse effect on the insulation.
- Any other condition occurs that would increase the likelihood of electric shock or fire, or both, during use of the equipment.

20 Marking

20.1 French

Where a product is intended for use in Canada, equipment shall additionally be marked in French in accordance with Annex [C](#).

20.2 General

Electrical equipment shall be legibly marked in accordance with Item a) and, where applicable, with Items b) and c) as well:

- a) The marking for a certified assembly shall be in the form of a nameplate permanently attached to the assembly. The marking for a certified component may be permitted to be in the form of a permanently attached nameplate or shall be made by permanent silk-screening or hot stamping, or by other permanent and legible means. The marking shall specify the following:
 - i) indication of certification, which shall include “CSA B44.1/ASME A17.5”;
 - ii) the manufacturer’s name, trademark, or a file number by which the organization responsible for the product may be identified;
 - iii) the complete electrical rating as described in Clause [20.4](#);
 - iv) the catalogue number, type, or equivalent for identification of the product; and
 - v) the temperature rating of the field-installed conductors for which the unit has been investigated except devices rated 30 A or less, or horsepower-rated devices having equivalent current rating of 24 A or less (see Tables [11](#) and [20](#)), which have been tested when wired with 60 °C or 60/75 °C conductors, need not be marked.

Equipment may be additionally marked to indicate higher-temperature-rated field-installed conductors are permitted provided the higher-rated conductors have a cross-sectional area no smaller than the cross-sectional area that would be required if 60 °C or 75 °C conductors were used.

Note: Examples of markings include

- a) “Use 60 C wire only”;
 - b) “Use 60 C/75 C wire only”; and
 - c) “Size wire per ampacity for 60 C/75 C”.
- b) Permanent or temporary (i.e., removable, “throw-away” labels or strip-off adhesive) nameplates shall be used to specify
 - i) instructions as to the method of installation to be followed or precautions to be observed when installing; and
 - ii) details of parts supplied loose to be fitted together during installation.
 - c) Separate drawings or manuals specifying installation information, setting and adjustments, wiring diagrams, etc., shall be provided where this data cannot be included in the assembly due to lack of space. This information may be provided separately or be installed in a permanent-type pocket located inside one or all of the compartments. If all the information is located in one compartment, the door concerned shall be marked to indicate the location of the pocket.

Notes:

- 1) Individual components are not required to be marked if the entire assembly is marked.
- 2) Wiring temperature ratings are only in SI (metric) units as this is the industry standard.

20.3 Copper or aluminum conductors

Electrical equipment for use with either copper or aluminum conductors shall be marked Cu-Al or the equivalent.

20.4 Electrical ratings

Unless otherwise indicated, electrical equipment shall be rated in volts, full-load amperes, volt-amperes, or any combination thereof. The rating shall indicate whether the equipment is for direct or alternating current. The rating of ac equipment shall include the number of phases and, if necessary, the frequency except the rating of equipment obviously intended for single-phase use only need not include the phase rating.

20.5 Auxiliary device

The rating of an auxiliary device shall

- be in the form of a contact rating code designation in accordance with Tables 20 and 21;
- be in volts, amperes, and inrush amperes; or
- indicate the voltage and contain the words “standard duty” or “heavy duty”, or the abbreviation “SD” or “HD”, as applicable.

20.6 Polymeric enclosures

Marking on polymeric enclosures shall consist of the following or equivalent wording:

CAUTION: BONDING BETWEEN CONDUITS MUST BE PROVIDED.

Note: See Annex C for equivalent French wording.

20.7 Manual switching means

Manual switching means shall be clearly marked with the words “ON” and “OFF” or with symbols* to indicate the ON and OFF positions of switches or controls that have such positions unless the construction or application of the switch or control is such that marking is unnecessary.

* Symbols for ON and OFF are “I” and “O”, respectively.

20.8 Equipment with more than one source

Electrical equipment that is energized by more than one source and does not have means for disconnecting all ungrounded conductors within a single enclosure or compartment shall be permanently marked on the outside with the following or equivalent wording:

WARNING: MORE THAN ONE LIVE CIRCUIT. SEE DIAGRAM.

Notes:

- See Annex C for equivalent French wording.
- This clause does not apply to circuits of extra-low voltage.

20.9 Fuse replacement markings

The voltage rating, amperage rating, fuse manufacturer, and type designation of fuses used to provide overcurrent protection in control circuits shall be permanently and legibly marked adjacent to the fuseholder. When the fuse is identified by a class designation (e.g., Class CC, RK5, etc.), the fuse manufacturer and type designation may be replaced by the class designation (e.g., “1 A, 300 V, Class CC”).

Alternatively, this information may be marked in a permanent table or diagram readily visible in the equipment. When this method is used, the table or diagram shall also identify each fuse with a unique identifier that is also permanently marked adjacent to each fuseholder.

20.10 Screw-type terminals

Electrical equipment provided with screw-type terminals for field wiring connections shall be identified using the designation that is given in the wiring diagram. In addition, contactors, relays, switches, overloads, and power resistors shall be identified using the designations that are given in the wiring diagram.

20.11 Oil tank

An oil tank shall be marked to indicate the proper oil level.

20.12 Enclosures with open bottoms

Enclosures with open bottoms in accordance with Clause 7.1.6 shall be marked with the following or equivalent wording:

WARNING: WHEN MOUNTING ON OR OVER A COMBUSTIBLE SURFACE, A FLOOR PLATE OF AT LEAST 1.43 mm (0.056 in) GALVANIZED OR 1.6 mm (1/16 in) UNCOATED STEEL EXTENDING AT LEAST 150 mm (6 in) BEYOND THE EQUIPMENT ON ALL SIDES MUST BE INSTALLED.

Note: See Annex C for equivalent French wording.

This marking need not be permanent.

20.13 Control devices shipped in separate pieces

A control device that is shipped in a condition for assembly in the field shall have the separate pieces identified to ensure proper assembly.

20.14 A live heat sink and other exposed parts

A live heat sink or other part likely to be mistakenly identified as dead metal and exposed to persons shall be marked with the following or equivalent wording:

CAUTION: RISK OF ELECTRIC SHOCK — PLATES (or other wording describing the type of part) ARE LIVE — DISCONNECT POWER SUPPLY BEFORE SERVICING.

Note: See Annex C for equivalent French wording.

The marking shall be located on the live part so as to make the risk known before the part is likely to be touched.

20.15 Short-circuit current rating

Elevator control equipment incorporating components in the motor branch circuit shall be marked with the following:

SUITABLE FOR USE ON A CIRCUIT CAPABLE OF DELIVERING NOT MORE THAN _____ rms
SYMMETRICAL AMPERES, _____ VOLTS MAXIMUM.

The ampere rating shall not be more than the value for which the elevator control equipment being marked was tested or the lowest short-circuit rating of any component connected to a branch circuit.

20.16 Overload relay with a replaceable current element

An overload relay that has a replaceable current element, or control equipment incorporating such an overload relay, shall be permanently marked with the following or equivalent wording:

WARNING: THE OVERLOAD RELAY MUST BE REPLACED IF BURNOUT OF THE CURRENT ELEMENT OCCURS.

Note: See Annex C for equivalent French wording.

20.17 Grounding conductors No. 6 AWG or smaller

Where more than one grounding conductor No. 6 AWG or smaller is to be terminated in a single- or multi-conductor terminal that will accept a range of conductor sizes, the following marking or equivalent wording shall appear adjacent to the grounding terminal:

TWIST WIRES TOGETHER BEFORE INSERTING IN TERMINAL.

If the terminal is suitable for both copper and aluminum conductors, the following additional marking or equivalent wording shall also appear adjacent to the grounding terminal:

CU-AL, COPPER WIRES MUST NOT BE MIXED WITH ALUMINUM WIRES IN THE SAME TERMINAL HOLE.

Note: See Annex C for equivalent French wording.

20.18 General caution and warning

20.18.1 General

A cautionary marking shall be prefixed with the word “CAUTION” or “WARNING”, as applicable, in letters not less than 3.2 mm (0.125 in) high. The remaining letters of such marking, unless specified otherwise in individual marking requirements, shall not be less than 1.6 mm (0.063 in) high.

Note: See Annex C for equivalent French wording.

20.18.2 Language

Markings prefixed with the words “CAUTION” or “WARNING” shall be provided in both English and French. Other markings shall be in English and may be in other languages.

Note: See Annex C for equivalent French wording.

20.19 Control with dc motor ratings

A control with dc motor ratings that does not comply with the requirements of Clause 15.1 d) i) shall be marked with the following or equivalent wording:

WARNING: DO NOT CONNECT TO A CIRCUIT SUPPLIED BY A SINGLE-PHASE, HALF-WAVE RECTIFIER.

Note: See Annex C for equivalent French wording.

A control that does not comply with the requirements of Clause 15.1 d) ii) shall be marked with the following or equivalent wording:

WARNING: DO NOT CONNECT TO A CIRCUIT SUPPLIED BY A SINGLE-PHASE RECTIFIER OF THE HALF-WAVE OR FULL-WAVE TYPE.

Note: See Annex C for equivalent French wording.

20.20 Markings for controllers according to Clause 13.1

With reference to the requirements in Clause 13.1, unless control circuit overcurrent protection is provided in the equipment, a permanent marking shall be provided on the controller or controller wiring diagram to indicate that such protection is sometimes necessary.

20.21 Power conversion equipment

20.21.1 General

In addition to the applicable markings of Clauses 20.2 to 20.20, power conversion equipment shall be marked as described in Clauses 20.21.2 to 20.21.8.

20.21.2 Motor overload protection

Marking for motor overload protection shall be as follows:

- a) Electrical equipment incorporating internal overload protection for the motor load and not requiring external or remote overload protection shall be marked to indicate the degree of

protection provided. The marking shall indicate the protection level as a percentage of the full-load current. If the protection level is adjustable, the marking shall be provided with instructions for adjustment.

- b) Equipment not incorporating internal overload protection for the motor load and intended for use with external or remote overload protection shall be marked to indicate that such protection is required.

20.21.3 Motor thermal protectors

Electrical equipment intended to be used with motors that have thermal protectors in or on the motors shall be marked to

- a) indicate the motors are required to have integral thermal protection; and
- b) identify the proper connection and the rating of the load imposed by the equipment on the protector contacts.

The rating shall be in volts and amperes except it shall be in volts or volt-amperes if the load is electromagnetic. The marking shall also indicate alternating or direct current.

20.21.4 Fuse replacement mark

Electrical equipment shall be marked to indicate the specific size, catalogue number, and manufacturer for replacement fuses. The equipment marking shall indicate at least one acceptable type fuse.

20.21.5 Specific overcurrent protective devices

Electrical equipment that is required to be connected to a supply source with a specific overcurrent protective device as specified in Clause [19.4.10](#) shall be marked to indicate the necessary protective device.

20.21.6 Wiring diagrams or instruction manuals

Markings in accordance with Clauses [20.21.2](#) to [20.21.5](#) may be provided on wiring diagrams or in instruction manuals that are supplied with the equipment and referenced on the nameplate or a similar marking that is permanently attached and visible after installation.

20.21.7 Overspeed protection

Power conversion equipment that does not incorporate overspeed protection shall be so marked.

20.21.8 Electronic over-temperature protection

Power conversion equipment not incorporating electronic over-temperature protection shall be so marked.

20.22 Controllers for platform lifts and chair lifts

Controllers for platform lifts and stair lifts for barrier-free access (see CSA B355), as well as those for platform lifts and stairway chairlifts (see ASME A18.1), shall be marked with the following or equivalent wording:

CONTROLLER FOR PLATFORM LIFTS AND STAIR LIFTS FOR BARRIER-FREE ACCESS.

or

CONTROLLER FOR PLATFORM LIFTS AND STAIRWAY CHAIRLIFTS.

Note: See Annex C for equivalent French wording.

20.23 Equipment marked with AGP

Equipment enclosures complying with both Clauses 5.3 and 7.2 may be marked with the additional indicator “AGP”. This marking shall be readily visible on the inside of the enclosure.

20.24 Controller with disconnecting means

Where a controller includes a disconnecting means and parts of the controller remain energized from a source other than the one disconnected (see Clause 12.5), a warning sign shall be mounted on or next to the disconnecting means. The sign shall be clearly legible and read as follows or use equivalent wording:

WARNING: PARTS OF THE CONTROLLER ARE NOT DE-ENERGIZED BY THIS SWITCH.

Note: See Annex C for equivalent French wording.

20.25 Controllers for wind turbine tower elevators

Controllers for wind turbine tower elevators shall be marked with the following or equivalent wording:

CONTROLLER FOR WIND TURBINE TOWER ELEVATORS.

Note: See Annex C for equivalent French wording.

20.26 Controllers for platform lifts or stair lifts for barrier-free access with an emergency power supply

Controllers for platform lifts or stair lifts provided with an emergency power supply for emergency lights in accordance with Clause 4.8.3 of CSA B355 or for an alarm in accordance with Clause 8.3.1 of CSA B355 shall be marked with the maximum allowable load in amps connected to the power supply.

Table 1
Thickness of sheet metal for enclosures — Carbon steel or stainless steel
 (See Clauses 4.3.1 to 4.3.3, 19.8.1, and 19.9.1.)

Without supporting frame*				With supporting frame or equivalent reinforcement*					
Maximum width†		Maximum length‡		Maximum width†		Maximum length‡		Minimum acceptable thickness, mm (in)	
mm	(in)	mm	(in)	mm	(in)	mm	(in)	Uncoated	Metal-coated
102	(4.0)	Not limited		159	(6.25)	Not limited		0.52 (0.020)	0.59 (0.023)
121	(4.75)	146	(5.75)	172	(6.75)	210	(8.25)		
152	(6.0)	Not limited		241	(9.5)	Not limited		0.68 (0.026)	0.75 (0.029)
178	(7.0)	222	(8.75)	254	(10.0)	318	(12.5)		
203	(8.0)	Not limited		305	(12.0)	Not limited		0.81 (0.032)	0.88 (0.034)
228	(9.0)	292	(11.5)	330	(13.0)	406	(16.0)		
318	(12.5)	Not limited		495	(19.5)	Not limited		1.07 (0.042)	1.16 (0.045)
356	(14.0)	457	(18.0)	533	(21.0)	635	(25.0)		
457	(18.0)	Not limited		686	(27.0)	Not limited		1.35 (0.053)	1.43 (0.056)
508	(20.0)	635	(25.0)	737	(29.0)	914	(36.0)		
559	(22.0)	Not limited		838	(33.0)	Not limited		1.52 (0.060)	1.62 (0.063)
635	(25.0)	787	(31.0)	889	(35.0)	1092	(43.0)		
635	(25.0)	Not limited		991	(39.0)	Not limited		1.70 (0.067)	1.79 (0.070)
737	(29.0)	965	(38.0)	1041	(41.0)	1295	(51.0)		

(Continued)

Table 1 (Continued)

Without supporting frame*				With supporting frame or equivalent reinforcement*					
Maximum width†		Maximum length‡		Maximum width†		Maximum length‡		Minimum acceptable thickness, mm (in)	
mm	(in)	mm	(in)	mm	(in)	mm	(in)	Uncoated	Metal-coated
838	(33.0)	Not limited		1295	(51.0)	Not limited		2.03 (0.080)	2.14 (0.084)
965	(38.0)	1194	(47.0)	1372	(54.0)	1676	(66.0)		
1067	(42.0)	Not limited		1626	(64.0)	Not limited		2.36 (0.093)	2.47 (0.097)
1194	(47.0)	1499	(59.0)	1727	(68.0)	2134	(84.0)		
1321	(52.0)	Not limited		2032	(80.0)	Not limited		2.74 (0.108)	2.85 (0.112)
1524	(60.0)	1680	(66.0)	2134	(84.0)	2616	(103.0)		
1600	(63.0)	Not limited		2464	(97.0)	Not limited		3.12 (0.123)	3.23 (0.127)
1854	(73.0)	2286	(90.0)	2616	(103.0)	3226	(127.0)		

* See Clause [4.3.3](#).

† The width is the smaller dimension of a rectangular piece of sheet metal that is part of an enclosure. Adjacent surfaces of an enclosure may have supports in common and be made of a single sheet.

‡ "Not limited" applies only if the edge of the surface is flanged at least 12.7 mm (0.5 in) or fastened to adjacent surfaces not normally removed in use.

Table 2
Thickness of sheet metal for enclosures — Aluminum, copper, or brass
 (See Clauses 4.3.1 to 4.3.3, 19.8.1, and 19.9.1.)

Without supporting frame*		With supporting frame or equivalent reinforcement*		Minimum acceptable thickness	
Maximum width†	Maximum length‡	Maximum width†	Maximum length‡		
mm	(in)	mm	(in)	mm	(in)
76	(3.0)	Not limited	178	(7.0)	Not limited
89	(3.5)	102	(4.0)	216	(8.5)
102	(4.0)	Not limited	254	(10.0)	Not limited
127	(5.0)	152	(6.0)	267	(10.5)
152	(6.0)	Not limited	356	(14.0)	Not limited
165	(6.5)	203	(8.0)	381	(15.0)
203	(8.0)	Not limited	483	(19.0)	Not limited
241	(9.5)	292	(11.5)	533	(21.0)
305	(12.0)	Not limited	711	(28.0)	Not limited
356	(14.0)	406	(16.0)	762	(30.0)
457	(18.0)	Not limited	1067	(42.0)	Not limited
508	(20.0)	635	(25.0)	1143	(45.0)
635	(25.0)	Not limited	1524	(60.0)	Not limited
737	(29.0)	914	(36.0)	1626	(64.0)
940	(37.0)	Not limited	2210	(87.0)	Not limited
1067	(42.0)	1346	(53.0)	2362	(93.0)
				2896	(114.0)
				310	(0.122)

(Continued)

Table 2 (Continued)

Without supporting frame*				With supporting frame or equivalent reinforcement*				Minimum acceptable thickness	
Maximum width†		Maximum length‡		Maximum width†		Maximum length‡			
mm	(in)	mm	(in)	mm	(in)	mm	(in)	mm	(in)
1321	(52.0)	Not limited		3124	(123.0)	Not limited			
1524	(60.0)	1880	(74.0)	3302	(130.0)	4064	(160.0)	3.89	(0.153)

* See Clause [4.3.3](#).

† The width is the smaller dimension of a rectangular piece of sheet metal that is part of an enclosure. Adjacent surfaces of an enclosure may have supports in common and be made of a single sheet.

‡ “Not limited” applies only if the edge of the surface is flanged at least 12.7 mm (0.5 in) or fastened to adjacent surfaces not normally removed in use.

Table 3
Size of bonding conductor
 (See Clause 6.9.)

Rating of circuit not exceeding, A	Size of bonding conductor		Size of metallic conduit or pipe, in	Size of electrical metallic tubing, in
	Copper wire, AWG	Aluminum wire, AWG		
15	14	12	1/2	1/2
20	12	10	1/2	1/2
30	10	8	1/2	1/2
40	10	8	1/2	1
60	10	8	3/4	1
100	8	6	1	1-1/4
200	6	4	1-1/4	1-1/2
300	4	2	1-1/4	1-1/2
400	3	1	2-1/2	2-1/2
500	2	0	2-1/2	2-1/2
600	1	00	3	4
800	0	000	4	4
1000	00	0000	4	4
1200	000	250 kcmil	6	—
1600	0000	350 kcmil	—	—
2000	250 kcmil	400 kcmil	—	—
2500	350 kcmil	500 kcmil	—	—
3000	400 kcmil	600 kcmil	—	—
4000	500 kcmil	800 kcmil	—	—
5000	700 kcmil	1000 kcmil	—	—
6000	800 kcmil	1250 kcmil	—	—

Table 4
Minimum acceptable distance from an opening to a part that can involve a risk of electric shock or injury to persons
 (See Clause [7.1.1](#).)

Minor dimension of opening, mm (in)*	Minimum distance from opening to part, mm (in)
25.4 (1.00)	165.0 (6.5)
31.8 (1.25)	190.0 (7.5)
38.1 (1.50)	318.0 (12.5)
47.6 (1.87)	394.0 (15.5)
54.0 (2.12)	444.0 (17.5)
†	762.0 (30.0)

* See Clause [7.1.4](#).

† More than 54.0 mm (2.12 in) but not more than 152.0 mm (6 in).

Table 5
Minimum spacings for live parts
 (See Clauses [7.1.6](#), [7.1.8](#), [16.1](#), [16.2](#), [16.6](#) to [16.8](#), [16.10](#), [16.11](#), [16.13](#), [16.16](#), [16.26.1](#), [16.26.2](#), [16.27.2](#), and [16.27.3](#).)

Group	Nominal voltage involved, V	Minimum spacings, mm (in)			
		Between bare live parts of opposite polarity and between bare live parts and grounded metal parts other than the enclosure		Between bare live parts and the walls of metal enclosures, including fittings for conduit or armoured cable*	
		Clearance	Creepage	Clearance	Creepage
A Control apparatus*	51–150	3.0 (0.12)†	6.3 (0.25)	12.7 (0.50)	12.7 (0.50)
	151–300	6.3 (0.25)	9.4 (0.37)	12.7 (0.50)	12.7 (0.50)
	301–600	9.4 (0.37)	12.7 (0.50)	12.7 (0.50)	12.7 (0.50)
	601–1000	14.0 (0.55)	21.6 (0.85)	20.3 (0.80)	25.4 (1.00)
	1001–1500	17.8 (0.70)	30.5 (1.20)	30.5 (1.20)	41.9 (1.65)
B Devices having limited ratings†	51–150	1.5 (0.06)†	1.5 (0.06)†	6.3 (0.25)	6.3 (0.25)
	151–300	1.5 (0.06)†	3.0 (0.12)†	6.3 (0.25)	6.3 (0.25)
	301–600	4.6 (0.18)†	9.4 (0.37)	12.7 (0.50)	12.7 (0.50)
C Other small devices†	51–150	3.0 (0.12)†	6.3 (0.25)	6.3 (0.25)	6.3 (0.25)
	151–300	6.3 (0.25)	6.3 (0.25)	6.3 (0.25)	6.3 (0.25)

(Continued)

Table 5 (Continued)

* For the purpose of this requirement, a metal piece attached to the enclosure is considered to be a part of the enclosure if deformation of the enclosure is likely to reduce spacings between the metal piece and uninsulated live parts.

† The spacing between wiring terminals of opposite polarity and the spacing between a wiring terminal and a grounded non-current-carrying metal part shall be not less than 6.3 mm (0.25 in) if short-circuiting or grounding of such terminals can result from projecting strands of wire.

‡ Spacings for components or equipment rated at voltages below 51 V are not specified but they shall be the subject of investigation.

Notes:

- 1) When measuring oversurface spacing, any slot, groove, or similar feature that is 0.33 mm (0.013 in) wide or less in the contour of insulating material shall be disregarded.
- 2) When measuring spacings, an air space of 0.33 mm (0.013 in) or less between a live part and an insulating surface shall be disregarded.

Table 6
Wire-bending space at the terminal of enclosed motor controllers
 (See Clause [8.1](#).)

Size of wire*, AWG or kcmil (mm ²)		Minimum bending space, terminal to wall, mm (in)		
		Wires per terminal		
		1	2	3
14–10	(2.1–8.3)	—	—	—
8–6	(8.4–13.3)	38 (1-1/2)	—	—
4–3	(21.2–26.7)	51 (2)	—	—
2	(33.6)	64 (2-1/2)	—	—
1	(42.4)	76 (3)	—	—
1/0	(53.5)	127 (5)	127 (5)	178 (7)
2/0	(67.4)	152 (6)	152 (6)	191 (7-1/2)
3/0	(85)	178 (7)	178 (7)	203 (8)
4/0	(107.2)	178 (7)	178 (7)	216 (8-1/2)
250	(127)	203 (8)	203 (8)	229 (9)
300	(152)	254 (10)	254 (10)	279 (11)
350	(177)	305 (12)	305 (12)	330 (13)
400	(203)	305 (12)	305 (12)	356 (14)
500	(253)	305 (12)	305 (12)	381 (15)
600	(304)	356 (14)	406 (16)	457 (18)
700	(355)	356 (14)	406 (16)	508 (20)

(Continued)

Table 6 (Continued)

Size of wire*, AWG or kcmil (mm ²)		Minimum bending space, terminal to wall, mm (in)		
		Wires per terminal		
		1	2	3
750–800	(380–405)	457 (18)	483 (19)	559 (22)
900	(456)	457 (18)	483 (19)	610 (24)

* The wire size shall be based on Clause [15.1 b](#)).

Table 7
Maximum acceptable rating of overcurrent device
 (See Clauses [13.2.1](#), [13.2.3](#), and [13.2.5](#).)

Rated primary current, A	Maximum rating of overcurrent protective device expressed as a percentage of the transformer primary current rating
Less than 2	300
2 to less than 9	167
9 or more	125*

* The next highest standard rating may be used if 125% of the current does not correspond to a standard rating of fuse or non-adjustable circuit breaker.

Table 8
Allowable ampacities of insulated copper conductors inside elevator electrical equipment enclosures based on a maximum ambient temperature of 40 °C
 (See Clause [14.1](#).)

Conductor size, AWG	Conductors with 90 °C insulation		Conductors with 105 °C insulation	
	In non-ventilated enclosure	In ventilated enclosure	In non-ventilated enclosure	In ventilated enclosure
Column 1	Column 2	Column 3	Column 4	Column 5
24	1	2	1	2
22	2	3	2	3
20	3	4	3	4
18	4	6	4	6
16	6	9	6	9
14	9	13	10	15
12	12	17	15	22

(Continued)

Table 8 (Continued)

Conductor size, AWG	Conductors with 90 °C insulation		Conductors with 105 °C insulation	
	In non-ventilated enclosure	In ventilated enclosure	In non-ventilated enclosure	In ventilated enclosure
Column 1	Column 2	Column 3	Column 4	Column 5
10	18	27	22	35
8	31	47	35	55
6	45	67	52	80
4	61	91	71	108
3	70	104	80	121
2	80	120	90	140
1	94	141	107	164
0	110	164	133	190
00	128	191	148	221
000	148	221	171	257
0000	173	258	200	300

Table 9
Ampacity correction factors for multiple conductor groupings
 (See Clause [14.1](#).)

Number of conductors	Correction factor
1–3	1.00
4–6	0.80
7–24	0.70
25–42	0.60
43 and more	0.50

Table 10
Full-load motor-running currents in amperes corresponding to various ac horsepower ratings
 (See Clauses [15.1](#) and [15.2](#).)

Horse- power	110–120 V			220–240 V			440–480 V			550–600 V		
	Single- phase	2- phase	3- phase	Single- phase	2- phase	3- phase	Single- phase	2- phase	3-phase	Single- phase	2-phase	3-phase
1/10	3.0	—	—	1.5	—	—	—	—	—	—	—	—
1/8	3.8	—	—	1.9	—	—	—	—	—	—	—	—
1/6	4.4	—	—	2.2	—	—	—	—	—	—	—	—
1/4	5.8	—	—	2.9	—	—	—	—	—	—	—	—
1/3	7.2	—	—	3.6	—	—	—	—	—	—	—	—
1/2	9.8	4.0	4.0	4.9	2.0	2.0	2.5	1.0	1.0	2.0	0.8	0.8
3/4	13.8	4.8	5.6	6.9	2.4	2.8	3.5	1.2	1.4	2.8	1.0	1.1
1	16.0	6.4	7.2	8.0	3.2	3.6	4.0	1.6	1.8	3.2	1.3	1.4
1-1/2	19.0	9.0	10.4	10.0	4.5	5.2	5.0	2.3	2.6	4.0	1.8	2.1
2	24.0	11.8	13.6	12.0	5.9	6.8	6.0	3.0	3.4	4.8	2.4	2.7
3	34.0	16.6	19.2	17.0	8.3	9.6	8.5	4.2	4.8	6.8	3.3	3.9
5	56.0	26.4	30.4	28.0	13.2	15.2	14.0	6.6	7.6	11.2	5.3	6.1
7-1/2	80.0	38.0	44.0	40.0	19.0	22.0	21.0	9.0	11.0	16.0	8.0	9.0
10	100.0	48.0	56.0	50.0	24.0	28.0	26.0	12.0	14.0	19.0	10.0	11.0
15	135.0	72.0	84.0	68.0	36.0	42.0	34.0	18.0	21.0	27.0	14.0	17.0
19	—	94.0	108.0	88.0	47.0	54.0	44.0	23.0	27.0	35.0	19.0	22.0
25	—	118.0	136.0	110.0	59.0	68.0	55.0	29.0	34.0	44.0	24.0	27.0
30	—	138.0	160.0	136.0	69.0	80.0	68.0	35.0	40.0	54.0	28.0	32.0

(Continued)

Table 10 (Continued)

Horse-power	110–120 V			220–240 V			440–480 V			550–600 V		
	Single-phase	2-phase	3-phase	Single-phase	2-phase	3-phase	Single-phase	2-phase	3-phase	Single-phase	2-phase	3-phase
40	—	180.0	198.0	176.0	90.0	104.0	88.0	45.0	52.0	70.0	36.0	41.0
50	—	226.0	260.0	216.0	113.0	130.0	108.0	56.0	65.0	86.0	45.0	52.0
60	—	—	—	—	133.0	154.0	—	67.0	77.0	—	53.0	62.0
75	—	—	—	—	166.0	192.0	—	83.0	96.0	—	66.0	77.0
100	—	—	—	—	218.0	248.0	—	109.0	124.0	—	87.0	99.0
125	—	—	—	—	—	312.0	—	135.0	156.0	—	108.0	125.0
150	—	—	—	—	—	360.0	—	156.0	180.0	—	125.0	144.0
190	—	—	—	—	—	480.0	—	198.0	240.0	—	167.0	192.0
250	—	—	—	—	—	602.0	—	—	302.0	—	—	242.0
300	—	—	—	—	—	—	—	—	361.0	—	—	289.0
350	—	—	—	—	—	—	—	—	414.0	—	—	336.0
400	—	—	—	—	—	—	—	—	477.0	—	—	382.0
500	—	—	—	—	—	—	—	—	590.0	—	—	472.0

Notes:

- 1) To obtain full-load currents for 190 and 198 V motors, increase corresponding 220–240 V ratings by 15% and 10%, respectively.
- 2) To obtain full-load currents for 265 and 277 V motors, decrease corresponding 220–240 V ratings by 13% and 17%, respectively.
- 3) These values of motor full-load current are for guidance only. Where exact values are required (e.g., for motor protection), always use those appearing on the motor nameplate.
- 4) These values of motor full-load current are for motors running at speeds usual for belted motors and motors with normal torque characteristics. Motors built for especially low speed or high torques may require more current, and multi-speed motors will have full-load current varying with speed, in which case the nameplate current rating shall be used.
- 5) For 90% and 80% power factor, multiply the above figures by 1.1 and 1.25, respectively.

Table 11
Full-load motor-running currents in amperes corresponding to various dc
horsepower ratings
 (See Clauses [15.1](#), [15.2](#), and [20.2](#).)

Horse-power	90 V	110–120 V	180 V	220–240 V	500 V	550–600 V
1/10	—	2.0	—	1.0	—	—
1/8	—	2.2	—	1.1	—	—
1/6	—	2.4	—	1.2	—	—
1/4*	4.0	3.1	2.0	1.6	—	—
1/3	5.2	4.1	2.6	2.0	—	—
1/2	6.8	5.4	3.4	2.7	—	—
3/4	9.6	7.6	4.8	3.8	—	1.6
1	12.2	9.5	6.1	4.7	—	2.0
1-1/2	—	13.2	8.3	6.6	—	2.7
2	—	17.0	10.8	8.5	—	3.6
3	—	25.0	16.0	12.2	—	5.2
5	—	40.0	27.0	20.0	—	8.3
7-1/2	—	58.0	—	29.0	13.6	12.2
10	—	76.0	—	38.0	18.0	16.0
15	—	110.0	—	55.0	27.0	24.0
20	—	148.0	—	72.0	34.0	31.0
25	—	184.0	—	89.0	43.0	38.0
30	—	220.0	—	106.0	51.0	46.0
40	—	292.0	—	140.0	67.0	61.0
50	—	360.0	—	173.0	83.0	75.0
60	—	—	—	206.0	99.0	90.0
75	—	—	—	255.0	123.0	111.0
100	—	—	—	341.0	164.0	148.0
125	—	—	—	425.0	205.0	185.0
150	—	—	—	506.0	246.0	222.0
200	—	—	—	675.0	330.0	294.0

* The full-load current for a 1/4 hp, 32 V dc motor is 8.6 A.

Table 12
Minimum conductor spacings (creepage and clearance) for printed circuit boards*
 (See Clauses [16.1](#), [16.9](#), [19.6.1](#), and [19.7.1](#).)

Volt [‡] ac rms or dc	Transient voltage not limited				Transient voltage limited			
	Coated [†]		Uncoated		Coated [†]		Uncoated	
	mm	(in)	mm	(in)	mm	(in)	mm	(in)
50 or less	0.18	(0.007)	0.85	(0.033)	0.025	(0.001)	0.04	(0.002)
51–100	0.25	(0.009)	1.00	(0.039)	0.10	(0.004)	0.16	(0.006)
101–125	0.28	(0.011)	1.05	(0.041)	0.16	(0.006)	0.25	(0.009)
126–150	0.32	(0.012)	1.10	(0.043)	0.25	(0.009)	0.40	(0.015)
151–200	0.42	(0.016)	1.40	(0.055)	0.40	(0.015)	0.63	(0.025)
201–250	0.56	(0.022)	1.80	(0.070)	0.56	(0.022)	1.00	(0.039)
251–320	0.75	(0.029)	2.20	(0.087)	0.75	(0.029)	1.60	(0.061)
321–400	1.00	(0.039)	2.80	(0.110)	1.00	(0.039)	2.00	(0.079)
401–500	1.30	(0.051)	3.60	(0.142)	1.30	(0.051)	2.50	(0.098)
501–630	1.80	(0.070)	4.50	(0.177)	1.80	(0.070)	3.20	(0.126)
631–800	2.40	(0.094)	5.60	(0.219)	2.40	(0.094)	4.00	(0.157)
801–1000	3.20	(0.126)	7.10	(0.279)	3.20	(0.126)	5.00	(0.197)

* The base material shall have a minimum CTI of 100.

† The coating shall comply with the requirements of Clause [19.6](#). Internal layers of PCBs shall be considered coated.

‡ Between the traces where spacing is measured.

Table 13
Minimum acceptable spacings for equipment for which transient voltages are known and controlled
 (See Clause 16.2.)

Short-circuit power	Peak working voltage	Minimum spacing, mm (in)					
		Between bare live parts of opposite polarity and between bare live parts and grounded parts other than the enclosure or exposed metal parts				Between any bare live parts and the walls of a metal enclosure, including fittings for conduit or armoured cable*	
		Through air or oil		Over surface		Through air	Over surface
More than 10 kVA for use where transient voltages are known and controlled	0–50	0.76	(0.030)	0.76	(0.030)	12.7 ⁺ (0.50)	6.3 (0.25)
	51–225	1.90	(0.075)	2.50	(0.100)	12.7 (0.50)	12.7 (0.50)
	226–450	3.80	(0.150)	5.10	(0.200)	12.7 (0.50)	12.7 (0.50)
	451–900	7.60	(0.300)	10.10	(0.39)	12.7 (0.50)	12.7 (0.50)
More than 500 VA but not more than 10 kVA [†]	0–30	0.76	(0.030)	0.76	(0.030)	12.7 ⁺ (0.50)	6.3 (0.25)
	31–50	0.76	(0.030)	0.76	(0.030)	12.7 ⁺ (0.50)	6.3 (0.25)
	51–225	1.52	(0.060)	1.52	(0.060)	12.7 (0.50)	12.7 (0.50)
	226–450	2.50	(0.100)	2.50	(0.100)	12.7 (0.50)	12.7 (0.50)
	451–900	5.10	(0.200)	5.10	(0.200)	12.7 (0.50)	12.7 (0.50)
500 VA or less [†]	0–36	0.30	(0.012)	0.30	(0.012)	12.7 ⁺ (0.50)	6.3 (0.25)
	37–72	0.40	(0.016)	0.40	(0.016)	12.7 ⁺ (0.50)	6.3 (0.25)
	73–100	0.76	(0.030)	0.76	(0.030)	12.7 ⁺ (0.50)	6.3 (0.25)
	101–225	1.14	(0.045)	1.14	(0.045)	12.7 (0.50)	12.7 (0.50)
	226–450	1.52	(0.060)	1.52	(0.060)	12.7 (0.50)	12.7 (0.50)
	451–900	2.50	(0.100)	2.50	(0.100)	12.7 (0.50)	12.7 (0.50)

(Continued)

Table 13 (Continued)

* A metal piece attached to the enclosure shall be considered to be part of the enclosure if deformation of the enclosure is likely to reduce spacings between the metal piece and uninsulated live parts. Spacings specified for parts other than enclosure walls shall be acceptable for metal walls of a sub-assembly mounted inside another enclosure if spacings in the sub-assembly are rigidly maintained.

† Where deflection of an enclosure wall cannot reduce the through-air spacing to the enclosure wall, the spacing through air may be 6.3 mm (0.25 in).

‡ Maximum short-circuit power is the product of the open-circuit voltage and the short-circuit current available at the supply terminals when protective devices are bypassed.

Notes:

- 1) When measuring an over-surface spacing, any slot, groove, or similar feature that is 0.33 mm (0.013 in) wide or less in the contour of insulating material shall be disregarded.
- 2) When measuring spacings, an air space of 0.33 mm (0.013 in) or less between a live part and an insulating surface shall be disregarded.

Table 14
Dimensions of bushings
 (See Clause [16.25](#).)

Trade size of conduits	Bushings dimensions, mm (in)	
	Overall diameter	Height
1/2	25.4 (1)	9.5 (3/8)
3/4	31.4 (1-15/64)	10.7 (27/64)
1	40.5 (1-19/32)	13.1 (33/64)
1-1/4	49.2 (1-15/16)	14.3 (9/16)
1-1/2	56.0 (2-13/64)	15.1 (19/32)
2	68.7 (2-45/64)	15.8 (5/8)
2-1/2	81.8 (3-7/32)	19.1 (3/4)
3	98.4 (3-7/8)	20.6 (13/16)
3-1/2	112.7 (4-7/16)	23.8 (15/16)
4	126.2 (4-31/32)	25.4 (1)
4-1/2	140.9 (4-35/64)	27.0 (1-1/16)
5	158.0 (6-7/32)	30.2 (1-3/16)
6	183.4 (7-7/32)	31.8 (1-1/4)

Table 15
Size and number of conductors per grounding termination
 (See Clause [17.4](#).)

Type of termination	Maximum conductor size, AWG	Maximum number of conductors
Binding head screw	No. 10	1
Screw with retaining means	No. 10	2
Wire connectors as per applicable wire connector standard:		
a) single conductor	As approved	1
b) multiple conductor	As approved	As approved
c) saddle clamp type	As approved	2

Note: Where a connector is certified for a range of conductor sizes, more than one conductor may be terminated in one connector provided the conductors are twisted together before being inserted in the connector and the equipment is so marked (see Clause [20.17](#)). Conductors larger than No. 6 AWG shall not be twisted together.