

INTERNATIONAL STANDARD



**Dynamic modules –
Part 5-1 Test methods – Dynamic gain tilt equalizer – Gain tilt settling time
measurement**

IECNORM.COM : Click to view the full PDF of IEC 62343-5-1:2014



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2014 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
Fax: +41 22 919 03 00
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

IEC Catalogue - webstore.iec.ch/catalogue

The stand-alone application for consulting the entire bibliographical information on IEC International Standards, Technical Specifications, Technical Reports and other documents. Available for PC, Mac OS, Android Tablets and iPad.

IEC publications search - www.iec.ch/searchpub

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and also once a month by email.

Electropedia - www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 30 000 terms and definitions in English and French, with equivalent terms in 14 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

More than 55 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: csc@iec.ch.

IECNORM.COM : Click to view the full PDF of IEC 60351-2014

INTERNATIONAL STANDARD



**Dynamic modules –
Part 5-1 Test methods – Dynamic gain tilt equalizer – Gain tilt settling time
measurement**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

PRICE CODE

R

ICS 33.180.01; 33.180.99

ISBN 978-2-8322-1959-1

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	4
1 Scope.....	6
2 Normative references	6
3 Terms, definitions, abbreviations and response waveforms.....	6
3.1 Terms and definitions.....	6
3.2 Abbreviations.....	7
3.3 Response waveforms.....	7
4 General information	8
5 Apparatus.....	9
5.1 Light source.....	9
5.2 Pulse generator	9
5.3 O/E converter	9
5.4 Temperature and humidity chamber.....	10
5.5 Oscilloscope	10
5.6 Temporary joints.....	10
5.7 Control system.....	10
5.8 Measurement setup	10
6 Procedure.....	11
6.1 Direct control type.....	11
6.1.1 Setup.....	11
6.1.2 Preparation.....	11
6.1.3 Wavelength setting	12
6.1.4 Pulse generator setting.....	12
6.1.5 Applying the driving pulse.....	12
6.1.6 Monitoring and recording the output signal from DGTE under test (DUT).....	12
6.1.7 Calculation of the gain tilt settling time	12
6.2 Digital control type.....	12
6.2.1 Setup.....	12
6.2.2 Preparation.....	12
6.2.3 Wavelength setting	12
6.2.4 Sending command.....	12
6.2.5 Monitoring and recording the command complete flag.....	13
6.2.6 Calculation of the gain tilt settling time	13
6.3 Analogue control type	13
6.3.1 Setup.....	13
6.3.2 Preparation.....	13
6.3.3 Wavelength setting	13
6.3.4 Applying the control signal.....	13
6.3.5 Monitoring and recording the command complete flag.....	13
6.3.6 Calculation of the gain tilt settling time	13
7 Details to be specified	13
7.1 Apparatus	13
7.1.1 Light source.....	13
7.1.2 Pulse generator	14
7.1.3 O/E converter	14
7.1.4 Control system	14

7.2 Measurement conditions	14
Annex A (informative) Convergence criterion	15
Annex B (informative) Measurement examples.....	16
Annex C (informative) Gain tilt settling time for specific DGTEs	17
Annex D (informative) Necessity for the correction for temperature dependency	18
Figure 1 – Response waveforms for direct control DGTEs	7
Figure 2 – Response waveforms for digital control DGTEs.....	8
Figure 3 – Response waveforms for analogue control DGTEs	8
Figure 4 – Measurement setup for direct control	10
Figure 5 – Measurement setup for digital control.....	11
Figure 6 – Measurement setup for analogue control.....	11
Figure B.1 – Where insertion loss change is sufficient	16
Figure B.2 – Where insertion loss change is small	16
Table 1 – Categorization of DGTE by the control method	9

IECNORM.COM : Click to view the full PDF of IEC 62343-5-1:2014

INTERNATIONAL ELECTROTECHNICAL COMMISSION

DYNAMIC MODULES –

**Part 5-1 Test methods – Dynamic gain tilt equalizer –
Gain tilt settling time measurement**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 62343-5-1 has been prepared by subcommittee 86C: Fibre optic systems and active devices, of IEC technical committee 86: Fibre optics.

This second edition cancels and replaces the first edition published in 2009. It constitutes a technical revision. This edition includes the following significant technical changes with respect to the previous edition:

- a) change in the title
- b) changes in performance parameter names.

The text of this standard is based on the following documents:

CDV	Report on voting
86C/1249/CDV	86C/1277/RVC

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts in the IEC 62343 series, published under the general title *Dynamic Modules*, can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

A bilingual version of this publication may be issued at a later date.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

DYNAMIC MODULES –

Part 5-1 Test methods – Dynamic gain tilt equalizer – Gain tilt settling time measurement

1 Scope

This part of IEC 62343 contains the measurement method of gain tilt settling time for a dynamic gain tilt equalizer (DGTE) to change its gain tilt from an arbitrary initial value to a desired target value.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 62343, *Dynamic modules – General and guidance*

IEC 62343-1-3, *Dynamic modules – Part 1-3: Performance standards – Dynamic gain tilt equalizer (non-connectorized)*

3 Terms, definitions, abbreviations and response waveforms

3.1 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 62343 and IEC 62343-1-3 and the following apply.

3.1.1

T_c

convergence time

time to converge from the first hit at the target $\pm Y\%$ to the stay within the deviation $\pm Y\%$ in the optical power from the output port of DGTE at pre-determined wavelength

3.1.2

T_l

latency time

<direct and analogue control types> time between the application of control signal and the change in output optical power by $\pm X\%$ of the initial power of DGTE at pre-determined wavelength

3.1.3

T_p

processing time

<digital control type> time between the application of control command and the change in output optical power by $\pm X\%$ of the initial power of DGTE at pre-determined wavelength

3.1.4

gain tilt settling time

$(T_l \text{ or } T_p) + T_r + T_c$

3.1.5 T_r **rise time**

time to change from the initial $\pm X\%$ to the target $\pm Y\%$ in the optical power from the output port of DGTE at pre-determined wavelength

3.1.6 T_s **settling time**


time to be suppressed from the first hit at the target $\pm Y\%$ to the final stay at the target within a required resolution of the optical power from the output port of DGTE at pre-determined wavelength

3.2 Abbreviations

CPU	central processing unit
DGTE	dynamic gain tilt equalizer
DUT	device under test
LCD	liquid crystal display
O/E	optical-to-electrical
PDL	polarization dependent loss
TLS	tuneable laser source
WDM	wavelength division multiplexing

3.3 Response waveforms

The definitions and symbols defined in 3.1 are shown in Figure 1, Figure 2 and Figure 3.



IEC

Figure 1 – Response waveforms for direct control DGTEs




Figure 2 – Response waveforms for digital control DGTEs







Figure 3 – Response waveforms for analogue control DGTEs

4 General information

The DGTE is categorized into three control methods as shown in Table 1. The direct control type is driven directly by voltage or current; the digital control type is operated by digital control system with digital signals; and the analogue control type is operated by analogue signals. The definition and the measurement method of gain tilt settling time for DGTE are different for the three control types. Table 1 also shows the configuration of operating systems and the correction for temperature dependency for three control types of DGTE. When the gain tilt settling time for the DGTE has temperature dependency, users may need to calibrate the temperature effect. The bottom row in Table 1 indicates the typical methods of the correction for temperature dependency (refer to Annex D).

Table 1 – Categorization of DGTE by the control method

	Direct control	Digital control	Analogue control
Control	By voltage or current directly	By command through digital circuit	By voltage or current through analogue circuit
Configurations			
Correction for temperature dependency	By control system	By digital circuit or control system	By analogue circuit or control system

5 Apparatus

5.1 Light source

A tuneable wavelength device is used as the light source. A tuneable laser source (TLS) or a combination of a broadband light source and tuneable filter is the typical equipment of tuneable wavelength light source. The tuning range of the tuneable wavelength light source shall be enough to cover the operating wavelength of DGTE to be measured.

In order to minimise the measurement uncertainty caused by the linewidth of the light source, the linewidth multiplied by the maximum value of the gain tilt slope of DGTE shall be smaller than one tenth of the dynamic gain tilt range. Typical value of operating wavelength range and dynamic gain tilt range of DGTE are 35 nm and ± 4 dB respectively. For example, the error for the linewidth of 1 nm is calculated as:

$$1 \times \left\{ \frac{4/35}{[+4 - (-4)]} \right\} = 1,4\% \quad (1)$$

The output power of the light source shall remain stable during the measurement. The stability of the output power during the gain tilt settling time of DGTE to be measured shall be smaller than one tenth of dynamic gain tilt range of DGTE.

If the polarization dependent loss (PDL) of DGTE to be measured is larger than 0,5 dB, a depolarized light source shall be used.

5.2 Pulse generator

A pulse generator is used to drive DGTE to be measured. The shape of the pulse shall be rectangular to change the gain tilt. The intensity and width of the pulse shall be such to make the maximum tilt change defined as the specification of DGTE. The rise time/fall time of the rectangular pulse shall be shorter than 10 ns or one tenth of the rise time/fall time to be measured.

5.3 O/E converter

An O/E converter is used to convert the optical output power of DGTE to be measured to the electrical power to be observed by an oscilloscope. The bandwidth of O/E converter shall be from DC to greater than $10(1/T_r)$ Hz, where T_r is the rise time to be measured.

The maximum power input to the O/E converter before compression shall be 10 times more than the optical power to be measured.

5.4 Temperature and humidity chamber

The test setup shall include an environmental chamber capable of producing and maintaining the specified temperature and/or humidity.

5.5 Oscilloscope

The oscilloscope shall have a storage function and sufficient bandwidth and accuracy. It shall have at least two traces.

5.6 Temporary joints


This is a method, device, or mechanical fixture for temporarily aligning two fibre ends into a reproducible, low loss joint. It may be, for example, a precision V-groove vacuum chuck, micromanipulator or a fusion or mechanical splice. The stability of the temporary joint shall be compatible with the measurement precision required.

5.7 Control system

For the digital and the analogue control types, the control system is used to drive the DGTE. The specification is defined individually.


5.8 Measurement setup

The measurement setups for the three types of DGTE in Table 1 are shown in Figure 4, Figure 5 and Figure 6, respectively. For each type of control, a correction signal from the O/E converter output is applied to the DGTE.



IEC


Figure 4 – Measurement setup for direct control



IEC

NOTE Either command complete flag or command sending flag can be used

Figure 5 – Measurement setup for digital control



IEC

NOTE The control system provides a step signal to the DGTE.

Figure 6 – Measurement setup for analogue control

6 Procedure

6.1 Direct control type

6.1.1 Setup

The measurement setup is shown in Figure 4. The temperature after setting shall be kept stabilized and uniform in the chamber for the stable measurement. The light source, the pulse generator, the O/E converter and the oscilloscope shall be turned on for the measurement.

6.1.2 Preparation

Before starting the measurement, the setup shall be held constant for more than 1 h for stabilization.

6.1.3 Wavelength setting

The wavelength of the light source shall be set at the measuring wavelength. The measurement shall take place at three wavelengths: shortest, centre and longest wavelengths in the operating wavelength range. An alternative method is to measure at the wavelength at the maximum deviation in insertion loss.

6.1.4 Pulse generator setting

The voltage or current to drive from the minimum (maximum) tilt to maximum (minimum) shall be set. The minimum and the maximum states of tilt occur when the deviation in insertion loss takes the maximum value at the shortest or the longest wavelength within the operating wavelength.

6.1.5 Applying the driving pulse

The driving pulse shall be applied to the DGTE to be measured by the pulse generator.

6.1.6 Monitoring and recording the output signal from DGTE under test (DUT)

The output signal from the O/E converter shall be monitored by the oscilloscope and the data shall be recorded. In addition, the signal pulse from the pulse generator shall be monitored and recorded.

6.1.7 Calculation of the gain tilt settling time

After the measurement at three wavelengths, the gain tilt settling time shall be calculated according to Figure 1. Generally, the gain tilt settling time is defined as the maximum value among the three gain tilt settling times.

6.2 Digital control type

6.2.1 Setup

The measurement setup is shown in Figure 5. The temperature after setting shall be kept stabilized and uniform in the chamber for the stable measurement. The light source, the digital control system, the O/E converter and the oscilloscope shall be turned on for the measurement.

6.2.2 Preparation

Before starting the measurement, the setup shall be turned on for more than 1 h for stabilization.

6.2.3 Wavelength setting

The wavelength of the light source shall be set at the measuring wavelength. The measurement shall take place at three wavelengths: shortest, centre and longest in the operating wavelength range. An alternative method is to measure at the wavelength at the maximum deviation in insertion loss.

6.2.4 Sending command

The command to operate from the minimum (maximum) tilt to maximum (minimum) shall be set. The minimum and the maximum states of tilt are given when the deviation in insertion loss takes the maximum value at the shortest or the longest wavelength within the operating wavelength. After the setting, the command shall be sent from the control system.

6.2.5 Monitoring and recording the command complete flag

The output signal from the O/E converter and the command complete flag from the DUT shall be monitored by the oscilloscope and the data shall be recorded. The command sending flag from the control system, which may be substituted for the command complete flag from DUT if not available, shall also be monitored and recorded.

6.2.6 Calculation of the gain tilt settling time

After the measurement at three wavelengths, the gain tilt settling time is calculated according to Figure 2. Generally, the gain tilt settling time is defined as the maximum value among the three gain tilt settling times.

6.3 Analogue control type

6.3.1 Setup

The measurement setup is as shown in Figure 5. The temperature shall be kept stabilized and constant in the chamber for the measurement. The light source, the analogue control system, O/E converter and oscilloscope shall be turned on for the measurement.

6.3.2 Preparation

Before starting the measurement, the setup shall be turned on for more than 1 h for stabilization.

6.3.3 Wavelength setting

The wavelength of the light source shall be set at the measuring wavelength. The measurement shall take place at three wavelengths: shortest, centre and longest wavelengths in the operating wavelength range. An alternative method is to measure at the wavelength at the maximum deviation in insertion loss.

6.3.4 Applying the control signal

The control signal to operate from the minimum (maximum) tilt to maximum (minimum) tilt shall be set. The minimum and the maximum states of tilt occur when the deviation in insertion loss takes the maximum value at the shortest or the longest wavelength within the operating wavelength. After the setting, the signal shall be sent from the control system.

6.3.5 Monitoring and recording the command complete flag

The output signal from the O/E converter shall be monitored by the oscilloscope and the data recorded. Also, the command complete flag from the control system shall be monitored and recorded.

6.3.6 Calculation of the gain tilt settling time

The gain tilt settling time is calculated according to Figure 3. After the measurement at three wavelengths, the gain tilt settling time is calculated. Generally, the gain tilt settling time is defined as the maximum value among the three gain tilt settling times.

7 Details to be specified

7.1 Apparatus

7.1.1 Light source

These characteristics of the light source shall be specified:

- spectral width
- state of polarization
- output power

7.1.2 Pulse generator

These characteristics of the pulse generator shall be specified:

- rising time
- pulse width
- pulse intensity

7.1.3 O/E converter

These characteristics of the O/E converter shall be specified:

- response frequency
- dynamic range

7.1.4 Control system

These characteristics of the control system shall be specified:

- type of control system
- type of interface

7.2 Measurement conditions

These measurement conditions shall be specified:

- wavelength
- deviation of tilt
- insertion loss deviation at the measuring wavelength
- temperature of chamber
- tolerance of target insertion loss deviation

IECNORM.COM Click to view the full PDF of IEC 62343-5-1:2014

Annex A (informative)

Convergence criterion

A DGTE used in an optical amplifier converts input signals with time-varying gain tilt into output signals in which gain tilt is nominally flat. A required flatness for multichannel EDFAs for WDM systems is typically $\pm 0,5$ dB for each spectral band. Therefore, the gain tilt settling time of the DGTE is recommended to be defined as the convergence to $\pm 0,5$ dB [$\cong (\pm 10 \%)$] from target attenuation.

IECNORM.COM : Click to view the full PDF of IEC 62343-5-1:2014