



**International  
Standard**

**ISO/IEC 7816-3**

**Identification cards — Integrated  
circuit cards —**

Part 3:  
**Cards with contacts — Electrical  
interface and transmission  
protocols**

AMENDMENT 1: Additional voltage  
classes

**Third edition  
2006-11-01**

**AMENDMENT 1  
2025-03**

IECNORM.COM : Click to view the full PDF of ISO/IEC 7816-3:2006/AMD1:2025



**COPYRIGHT PROTECTED DOCUMENT**

© ISO/IEC 2025

All rights reserved. Unless otherwise specified, or required in the context of its implementation, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office  
CP 401 • Ch. de Blandonnet 8  
CH-1214 Vernier, Geneva  
Phone: +41 22 749 01 11  
Email: [copyright@iso.org](mailto:copyright@iso.org)  
Website: [www.iso.org](http://www.iso.org)

Published in Switzerland

## Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular, the different approval criteria needed for the different types of document should be noted. This document was drafted in accordance with the editorial rules of the ISO/IEC Directives, Part 2 (see [www.iso.org/directives](http://www.iso.org/directives) or [www.iec.ch/members\\_experts/refdocs](http://www.iec.ch/members_experts/refdocs)).

ISO and IEC draw attention to the possibility that the implementation of this document may involve the use of (a) patent(s). ISO and IEC take no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, ISO and IEC had not received notice of (a) patent(s) which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at [www.iso.org/patents](http://www.iso.org/patents) and <https://patents.iec.ch>. ISO and IEC shall not be held responsible for identifying any or all such patent rights.

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation of the voluntary nature of standards, the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT) see [www.iso.org/iso/foreword.html](http://www.iso.org/iso/foreword.html). In the IEC, see [www.iec.ch/understanding-standards](http://www.iec.ch/understanding-standards).

This document was prepared by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 17, *Cards and security devices for personal identification*.

A list of all parts in the ISO/IEC 7816 series can be found on the ISO and IEC websites.

Any feedback or questions on this document should be directed to the user's national standards body. A complete listing of these bodies can be found at [www.iso.org/members.html](http://www.iso.org/members.html) and [www.iec.ch/national-committees](http://www.iec.ch/national-committees).

IECNORM.COM : Click to view the full PDF of ISO/IEC 7816-3:2006/AMD1:2025

## Identification cards — Integrated circuit cards —

### Part 3:

## Cards with contacts — Electrical interface and transmission protocols

### AMENDMENT 1: Additional voltage classes

Clause 4, second line

Replace “A, B, C” by “A, B, C, D”

5.1.3, paragraph 1

Replace “three classes” by “four classes”, and add a 4<sup>th</sup> dash with content: “1,2 V for class D.”

5.2.1, Table 1

Replace Table 1 with the following:

**Table 1 — Electrical characteristics of VCC under normal operating conditions**

Symbol	Condition	Minimum	Maximum	Unit
$U_{CC}$	Class A (5,0 V nominal)	4,5	5,5	V
	Class B (3,0 V nominal)	2,7	3,3	
	Class C (1,8 V nominal)	1,62	1,98	
	Class D (1,2 V nominal)	1,10	1,30	
$I_{CC}^a$	Class A, at maximum allowed frequency		60	mA
	Class B, at maximum allowed frequency		50	
	Class C, at maximum allowed frequency		30	
	Class D, at maximum allowed frequency		60	
	When the clock is stopped, see 6.3.2		0,5	

<sup>a</sup> The current value is averaged over 1 ms.

5.2.1, Table 2

In the second column replace “nA.s” by “nA s” (i.e. remove the dot between nA and s).

5.2.1, Table 2

Add another row to Table 2 immediately below the rows for Class C with the following content:

D	12 nA s	400 ns	60 mA
---	---------	--------	-------

5.2.3, Table 4

In the second column, row three, replace “Class C” by “Class C and class D”.

5.2.5, Table 5

Replace the row for  $U_{OL}$  in Table 5 by the following and add table footnote b:

$U_{OL}$	$I_{OL} = 1 \text{ mA}$ for class A <sup>a</sup> and class B <sup>a</sup> $I_{OL} = 500 \text{ }\mu\text{A}$ for class C <sup>a</sup>	0	$0,15 U_{CC}$	V
	$I_{OL} = 1 \text{ mA}$ for class D	0 <sup>b</sup>	0,2	V
<sup>b</sup> To allow for overshoot the voltage on I/O shall remain between $-0,3 \text{ V}$ and $U_{CC} + 0,3 \text{ V}$ during dynamic operation.				

6.2.1, paragraph 1

Replace “A, B or C” by “A, B, C or D”.

8.3

Replace the paragraph above Table 9, the indented paragraph between Table 9 and Table 10, and Table 10 with the following text:

**The first TA for T=15** encodes the clock stop indicator (X) and the class indicator (Y) as specified in Table 9. The default values are X = “clock stop not supported” and Y = “only class A supported”. For the use of clock stop, see 6.3.2. For the use of the classes of operating conditions, see 6.2.1 and 6.2.4.

Replace Table 9 with the following:

**Table 9 — Clock stop indicator (X) and class indicator (Y)**

b8	b7	b6	b5	b4	b3	b2	b1	Value
x	x	-	-	-	-	-	-	<b>Clock stop indicator (X)</b>
0	0	-	-	-	-	-	-	Clock stop not supported (default value)
0	1	-	-	-	-	-	-	State L
1	0	-	-	-	-	-	-	State H
1	1	-	-	-	-	-	-	No preference
-	-	x	x	x	x	x	x	<b>Class indicator (Y)</b>
-	-	0	0	0	0	0	1	Only class A supported
-	-	0	0	0	0	1	0	Only class B supported
-	-	0	0	0	1	0	0	Only class C supported
-	-	0	0	1	0	0	0	Only class D supported
-	-	0	0	0	0	1	1	Only classes A and B supported
-	-	0	0	0	1	1	0	Only classes B and C supported
-	-	0	0	1	1	0	0	Only classes C and D supported
-	-	0	0	0	1	1	1	Only classes A, B and C supported
Any other value								RFU