

First edition
1996-08-01

AMENDMENT 1
2000-12-15

**Information technology — Open Systems
Interconnection — Connectionless Session
protocol: Protocol specification**

AMENDMENT 1: Efficiency enhancements

*Technologies de l'information — Interconnexion de systèmes ouverts
(OSI) — Protocole de service de session en mode sans connexion:
Spécification du protocole*

AMENDEMENT 1: Améliorations du rendement

IECNORM.COM : Click to view the full PDF of ISO/IEC 9548-1:1996/Amd 1:2000

Reference number
ISO/IEC 9548-1:1996/Amd.1:2000(E)



PDF disclaimer

This PDF file may contain embedded typefaces. In accordance with Adobe's licensing policy, this file may be printed or viewed but shall not be edited unless the typefaces which are embedded are licensed to and installed on the computer performing the editing. In downloading this file, parties accept therein the responsibility of not infringing Adobe's licensing policy. The ISO Central Secretariat accepts no liability in this area.

Adobe is a trademark of Adobe Systems Incorporated.

Details of the software products used to create this PDF file can be found in the General Info relative to the file; the PDF-creation parameters were optimized for printing. Every care has been taken to ensure that the file is suitable for use by ISO member bodies. In the unlikely event that a problem relating to it is found, please inform the Central Secretariat at the address given below.

IECNORM.COM : Click to view the full PDF of ISO/IEC 9548-1:1996/Amd 1:2000

© ISO/IEC 2000

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Case postale 56 • CH-1211 Geneva 20
Tel. + 41 22 749 01 11
Fax + 41 22 749 09 47
E-mail copyright@iso.ch
Web www.iso.ch

Printed in Switzerland

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work.

International Standards are drafted in accordance with the rules given in the ISO/IEC Directives, Part 3.

In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1. Draft International Standards adopted by the joint technical committee are circulated to national bodies for voting. Publication as an International Standard requires approval by at least 75 % of the national bodies casting a vote.

Attention is drawn to the possibility that some of the elements of this Amendment may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights.

Amendment 1 to International Standard ISO/IEC 9548-1:1996 was prepared by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, in collaboration with ITU-T. The identical text is published as ITU-T Rec. X.235/Amd.1.

IECNORM.COM : Click to view the full PDF of ISO/IEC 9548-1:1996/Amd 1:2000

Introduction

This amendment is one of a set of amendments to the OSI upper-layers standards produced to facilitate the interconnection of information processing systems in an open environment where efficiency of communications is paramount. Such efficiencies include:

- a) reduction in the overhead needed to encode control information for use in bandwidth-limited environments (such as radio links) or processing-limited systems (such as switching systems);
- b) reduction in the delay to set up the association between the communicating applications, so that data transfer can begin expeditiously;
- c) reduction in the support of unneeded functionality in certain environments where the communications requirements of the applications are limited.

This amendment modifies the connectionless Session Protocol to support the "short-encoding" protocol option. The short-encoding option provides alternative and smaller protocol control information for the connectionless-mode session protocol data units.

IECNORM.COM : Click to view the full PDF of ISO/IEC 9548-1:1996/Amd 1:2000

INTERNATIONAL STANDARD

ITU-T RECOMMENDATION

**INFORMATION TECHNOLOGY – OPEN SYSTEMS INTERCONNECTION –
CONNECTIONLESS SESSION PROTOCOL:
PROTOCOL SPECIFICATION**

AMENDMENT 1

Efficiency enhancements

1) Subclause 2.1

Add the following reference by numerical order:

- ITU-T Recommendation X.215 (1995)/Amd.1 (1997) | ISO/IEC 8326:1996/Amd.1:1998, *Information technology – Open Systems Interconnection – Session Service Definition – Amendment 1: Efficiency enhancements.*

2) Subclause 3.2

Add the following definitions after 3.2.2:

3.2.3 Long-form SPDU: An SPDU that has the long-form structure defined in 7.2.

3.2.4 Short-form SPDU: An SPDU that has the short-form structure defined in 7.4. All short-form SPDUs have names that begin with the word **SHORT** and abbreviations beginning with the letter **S**.

3.2.5 Short-encoding protocol option: An option of the session protocol that permits the use of smaller protocol control information of the Session SPDUs in the data transfer phase.

3.2.6 Parameter indication: A field in the low-order bits of the first octet of a short-form SPDU (the high-order bits will contain the SPDU identifier).

3) Subclause 4.2

Add the following abbreviation by alphabetical order:

SUD SPDU Short Unit Data SPDU

4) Subclause 4.3

Add the following abbreviation by alphabetical order:

SI&P SPDU identifier (for short-form SPDUs) and parameter indication

5) Subclause 6.1.3

Add the following SPDU at the beginning of the list:

SHORT-UNIT-DATA SUD

6) Subclause 6.2.3

Add the following at the beginning of the list:

SUD SPDU
 user data

7) Subclause 6.2.4

Add the following to 6.2.4:

The UNIT-DATA SPDU is transmitted when the initiating SPM has chosen not to use a SHORT-UNIT-DATA SPDU.

8) New subclauses 6.2.6 and 6.2.7

Add the following two new subclauses after 6.2.5:

6.2.6 Sending a SUD SPDU

The initiating SPM can choose to use the SHORT-UNIT-DATA SPDU if in the parameters of the S-UNIT-DATA request the Called Session Address and Calling Session Address have NIL values of the Called and Calling Session Selectors.

The Called and Calling Session Address parameters of the S-UNIT-DATA request service primitive are used to determine the source and destination addresses.

If the length of the SPDU exceeds the maximum TSDU size supported by the transport service, then the S-UNIT-DATA request is discarded and a local report may be made to the SS-user indicating the inability of the session layer to provide the service requested.

A SUD SPDU is constructed with the user data supplied by the SS-user in the S-UNIT-DATA request.

The SHORT-UNIT-DATA SPDU is transmitted on the User-data of a T-UNIT-DATA request primitive.

A T-UNIT-DATA request service primitive is issued with the source and destination addresses determined above, the Quality of Service requested and a TS-user-data parameter containing the SHORT-UNIT-DATA SPDU.

6.2.7 Receiving a SUD SPDU

The SUD SPDU arrives in the TS-user-data field of a T-UNIT-DATA indication.

If the receiving SPM does not support the short-encoding protocol option and the SHORT-UNIT-DATA SPDU is received as user data on a T-UNIT-DATA indication primitive, it shall discard the SPDU without any notification.

A valid incoming SHORT-UNIT-DATA SPDU results in an S-UNIT-DATA indication.

The source address from the T-UNIT-DATA indication and the NIL session selector will be used to determine the calling session address parameter for the S-UNIT-DATA indication. The destination address from the T-UNIT-DATA indication and the NIL session selector will be used to determine the called session address parameter for the S-UNIT-DATA indication.

The user information field of the SUD SPDU will be mapped to the user data parameter of the S-UNIT-DATA indication.

If the data cannot be immediately delivered to a SS-user due to non-existent recipient, recipient not ready to receive, or too large data field size, that unit data is discarded without any notification.

9) Clause 7

Change the title of clause 7 to:

7 Encoding of the unit data SPDUs

10) Subclause 7.2

a) *Change title of subclause 7.2 to:*

7.2 SPDU structure (long form SPDU)

b) *Change the first sentence of 7.2, based on the underlined additions, as follows:*

This subclause specifies the general structure of long-form SPDUs in terms of their constituent fields. Long-form SPDUs are all SPDUs whose names do not begin with "SHORT".

c) *Add long-form in front of SPDU throughout the rest of 7.2.*

11) Subclauses 7.2.1 through 7.2.5

Add long-form in front of SPDU wherever it occurs in 7.2.1 through 7.2.5.

12) Subclause 7.3

Change title of 7.3 to:

7.3 SPDU identifiers and associated parameter fields (long form SPDU)

13) New subclauses 7.4 and 7.5

Add the following two new subclauses after 7.3:

7.4 SPDU structure (short-form SPDUs)

This subclause specifies the general structure of short-form SPDUs in terms of their constituent fields. Short-form SPDUs are all SPDUs whose names begin with "SHORT". The general structure for such SPDUs is illustrated in Table 4.

Codings and structural requirements specific to particular short-form SPDUs are specified in 7.5.

Examples of valid short-form SPDU structure are illustrated in Table 4.

Table 4 – Short-form SPDU structure

Short-form SPDUs	SI&P field	Parameter field	User-information field
SI&P octet	i i i i 0 0 0		

7.4.1 Short-form SPDUs

Short-form SPDUs shall contain, in the following order:

- a) an SI&P field of one octet;
- b) the User-information field, if defined for the SPDU and if present.

The SI&P octet contains the following field:

- c) The SI field in bits 4-8, shown as "i" in Table 4. This identifies the type of short-form SPDU; the high-order bit (bit 8 of the SI&P octet) is 1 for all short-form SPDUs.

The overall length of a short-form SPDU is determined by the TSDU length.

7.4.2 User-information fields

Following the SI&P octet and any fixed length parameters, the User-information field of the short-form SPDU shall contain the SSDU. The order of the octets and the order of the bits in the SSDU shall be maintained in the SPDU.

7.5 Short-form SPDU identifiers and associated parameter fields

All short-form SPDUs have SI fields of 5 bits, in which the high-order bit (bit 8 of the SI&P field) is 1.

The short-form SPDUs specified in the remainder of this subclause have SI fields of five bits. These are represented in this subclause as bit strings, using the notation:

"VWXYZ"b

where each of "V", "W", "X", "Y", "Z" is either a "0" or "1". In the SI&P octet of the short-form SPDU:

- The value shown in position V represents bit 8 of the SI&P octet;
- The value shown in position W represents bit 7 of the SI&P octet;
- The value shown in position X represents bit 6 of the SI&P octet;
- The value shown in position Y represents bit 5 of the SI&P octet;

The value shown in position Z represents bit 4 of the SI&P octet.

NOTE – Bit 8 (V) is 1 for all short-form SPDUs (and bit 8 is always zero in the SI octet of a long-form SPDUs). For most, but not all, short-form SPDUs, WXYZ is the same as the low-order four bits of the SI of the corresponding long-form SPDU.

7.5.1 SHORT-UNIT-DATA (SUD) SPDU

7.5.1.1 The SI field of the SI&P octet shall contain "11000"b.

7.5.1.2 Bit 3 of the SI&P octet shall contain the parameter indication, as specified in 7.4.2.

7.5.1.3 Bits 1 and 2 of the SI&P octet shall be zero.

7.5.1.4 Octet 2 and any following octets shall contain the User-information field.

NOTE – The SUD always has a length greater than one.