



INTERNATIONAL STANDARD ISO/IEC 9594-3:1998
TECHNICAL CORRIGENDUM 1

Published 2002-03-01

INTERNATIONAL ORGANIZATION FOR STANDARDIZATION • МЕЖДУНАРОДНАЯ ОРГАНИЗАЦИЯ ПО СТАНДАРТИЗАЦИИ • ORGANISATION INTERNATIONALE DE NORMALISATION
INTERNATIONAL ELECTROTECHNICAL COMMISSION • МЕЖДУНАРОДНАЯ ЭЛЕКТРОТЕХНИЧЕСКАЯ КОМИССИЯ • COMMISSION ÉLECTROTECHNIQUE INTERNATIONALE

**Information technology — Open Systems Interconnection —
The Directory: Abstract service definition**

TECHNICAL CORRIGENDUM 1

Technologies de l'information — Interconnexion de systèmes ouverts (OSI) — L'annuaire: Définitions du service abstrait

RECTIFICATIF TECHNIQUE 1

Technical Corrigendum 1 to International Standard ISO/IEC 9594-3:1998 was prepared by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 6, *Telecommunications and information exchange between systems*.

STANDARDSISO.COM : Click to view the full PDF of ISO/IEC 9594-3:1998/Cor 1:2002

INTERNATIONAL STANDARD

ITU-T RECOMMENDATION

INFORMATION TECHNOLOGY – OPEN SYSTEMS INTERCONNECTION –
THE DIRECTORY: ABSTRACT SERVICE DEFINITION

TECHNICAL CORRIGENDUM 1

1) Resolution to defect report 9594/166

Subclause 7.11.1.1 Alias dereferencing

Change the second to last sentence of the first paragraph as follows:

If the DSA chains the request to another DSA and receives back a referral from it, then the access controls shall be applied to the referral if the targetObject in the referral is the same as in the chained request.

2) Resolution to defect report 9594/179

Annex B, Figure B.4

In the flow chart "Return of DN" add under the question "alias name available?/No" an additional question:

"Read operation?"

with the following outputs :

Yes: Name Error

No: *go to next question:* entry corresponds to (base) object of DAP operation?

Annex B, Figure B.5

In the flow chart "Read Operation" change on the right part the text of the last step of handling "selection empty = yes"

from:

"return Read result"

to:

"return Read result or nameError"

3) Resolution to defect report 9594/188

Subclause 11.1.5 Add operation decision points for basic-access-control

Reword NOTE 2 to read as follows:

"The Add permission must be provided as prescriptiveACI when attempting to add an entry, and as prescriptiveACI, or subentryACI, when attempting to add a subentry."

4) Resolution to defect report 9594/202

Subclause 7.10 Security Parameters

Replace the paragraph describing **CertificationPath** with the following:

The **CertificationPath** component is a sequence containing the signer's user certificate, and, optionally, a sequence of one or more certification authority (CA) certificates. (See clause 8 in ITU-T Rec. X.509 | ISO/IEC 9594-8). The user certificate is used to bind the signer's public key and distinguished name, and may be used to verify the signature on a request argument, response, or error. This parameter shall be present and contain the signer's user certificate if the request argument, response, or error is signed. Additional certificates may be present and may be used to determine if the signer's user certificate is valid. Additional certificates are not required if the recipient shares the same certification authority as the signer. If the recipient requires a certification path for validation, and an acceptable parameter is not present, whether the recipient rejects the signature, or attempts to determine a certification path, is a local matter.

Replace the paragraph describing **time** with the following:

The **time** is the intended expiry time for the validity of the request, response, or error. It is used in conjunction with the random number to enable the detection of replay attacks.

Replace the 1st paragraph in the paragraph describing **random** with the following:

The **random** value is a number that should be different for each request, response, or error. It is used in conjunction with the time parameter to enable the detection of replay attacks. If sequence integrity is required then the random argument may be used to carry a sequence integrity number as follows:

5) Resolution to defect report 9594/206

Subclause 10.1.3 List results

In the second to last paragraph, change the first part of the first sentence "When a DUA has requested a protection request of signed, the **uncorrelatedListInfo** parameter..." as follows:

"When the DUA has requested a protection request of signed, or if the Directory for other reasons are not able to correlate information, the **uncorrelatedListInfo** parameter..."

6) Resolution to defect report 9594/217

Subclause 7.10 Security parameters

Replace syntax for **operationCode** in **SecurityParameters** as follows:

operationCode [6] Code OPTIONAL

Code should be imported from:

Remote-Operations-Information-Objects

{joint-iso-ccitt remote-operations(4) informationObjects(5) version1(0)}

In the paragraph describing **operationCode** delete "object identifier". Also, at the end of the same paragraph, change:

"or results"

to:

"results or errors".

Add to the **SecurityParameters** syntax:

errorCode [9] Code OPTIONAL

and add the following description:

The **errorCode** is used to secure the error code where an error is returned in response to an operation.